

MAXIM

+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

General Description

The MAX706P/R/S/T and MAX708R/S/T microprocessor (μ P) supervisory circuits reduce the complexity and number of components required to monitor +3V power-supply levels in +3V to +5V μ P systems. These devices significantly improve system reliability and accuracy compared to separate ICs or discrete components.

The MAX706P/R/S/T supervisory circuits provide the following four functions:

- 1) A reset output during power-up, power-down, and brownout conditions.
- 2) An independent watchdog output that goes low if the watchdog input has not been toggled within 1.6sec.
- 3) A 1.25V threshold detector for power-fail warning, low-battery detection, or for monitoring a power supply other than the main supply.
- 4) An active-low manual-reset input.

The only difference between the MAX706R, MAX706S, and MAX706T is the reset-threshold voltage levels, which are 2.63V, 2.93V, and 3.08V, respectively. All have active-low reset output signals. The MAX706P is identical to the MAX706R, except its reset output signal is active-high.


The MAX708R/S/T provide the same functions as the MAX706R/S/T, except they do not have a watchdog timer. Instead, they provide both $\overline{\text{RESET}}$ and RESET outputs. As with the MAX706, devices with R, S, and T suffixes have reset thresholds of 2.63V, 2.93V and 3.08V, respectively.

All seven devices are offered in 8-pin SO, DIP, and μ MAX packages.

Applications

Battery-Powered Equipment
Portable Instruments
Computers
Controllers
Intelligent Instruments
Critical μ P Power Monitoring

Typical Operating Circuits



Features

- ♦ μ MAX Package: Smallest 8-Pin SO
- ♦ Precision Supply-Voltage Monitor
2.63V (MAX706P/R, MAX708R)
2.93V (MAX706S, MAX708S)
3.08V (MAX706T, MAX708T)
- ♦ 200ms Reset Time Delay
- ♦ Debounced TTL/CMOS-Compatible Manual-Reset Input
- ♦ 100 μ A Quiescent Current
- ♦ Watchdog Timer (MAX706P/R/S/T only):
1.6sec Timeout
- ♦ Reset Output Signal:
Active-High Only (MAX706P)
Active-Low Only (MAX706R/S/T)
Active-High and Active-Low (MAX708R/S/T)
- ♦ Voltage Monitor for Power-Fail or Low-Battery Warning
- ♦ 8-Pin Surface-Mount Package
- ♦ Guaranteed $\overline{\text{RESET}}$ Assertion to $V_{CC} = 1V$

Ordering Information

PART	TEMP. RANGE	PIN-PACKAGE
MAX706PCPA	0°C to +70°C	8 Plastic DIP
MAX706PCSA	0°C to +70°C	8 SO
MAX706PCUA	0°C to +70°C	8 μ MAX
MAX706PEPA	-40°C to +85°C	8 Plastic DIP
MAX706PESA	-40°C to +85°C	8 SO

Ordering Information continued at end of data sheet.

* Contact factory for availability and processing to MIL-STD-883.

Pin Configurations

TOP VIEW



DIP/SO



DIP/SO

Pin Configurations continued at end of data sheet.

MAXIM

Maxim Integrated Products 1

For pricing, delivery, and ordering information, please contact Maxim/Dallas Direct! at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

MAX706P/R/S/T, MAX708R/S/T

+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

ABSOLUTE MAXIMUM RATINGS

Terminal Voltage (with respect to GND)

VCC-0.3V to 6.0V

All Other Inputs (Note 1).....-0.3V to (VCC + 0.3V)

Input Current

VCC20mA

GND20mA

Output Current (all outputs)20mA

Continuous Power Dissipation

Plastic DIP (derate 9.09mW/°C above +70°C)727mW

SO (derate 5.88mW/°C above +70°C)471mW

μ MAX (derate 4.1mW/°C above +70°C)330mW

CERDIP (derate 8.00mW/°C above +70°C)640mW

Operating Temperature Ranges:

MAX70_C_0°C to +70°C

MAX70_E_-40°C to +85°C

MAX70_M_-55°C to +125°C

Storage Temperature Range-65°C to +160°C

Lead Temperature (soldering, 10s)+300°C

Note 1: The input voltage limits on PFI, WDI and \overline{MR} can be exceeded if the input current is less than 10mA.

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(MAX70_P/R: VCC = 2.70V to 5.5V, MAX70_S: VCC = 3.00V to 5.5V, MAX70_T: VCC = 3.15V to 5.5V, TA = TMIN to TMAX, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Operating Voltage Range	V _{CC}		MAX70_C	1.0		5.5	V
			MAX70_E/M	1.2		5.5	
Supply Current	I _{SUPPLY}	V _{CC} < 3.6V	MAX706_C		90	200	μA
			MAX706_E/M		90	300	
			MAX708_C		50	200	
			MAX708_E/M		50	300	
		V _{CC} < 5.5V	MAX706_C		135	350	
			MAX706_E/M		135	500	
			MAX708_C		65	350	
			MAX708_E/M		65	500	
Reset Threshold (Note 2)	V _{RST}		MAX70_P/R	2.55	2.63	2.70	V
			MAX70_S	2.85	2.93	3.00	
			MAX70_T	3.00	3.08	3.15	
Reset Threshold Hysteresis (Note 2)					20		mV
Reset Pulse Width (Note 2)	t _{RST}	MAX70_P/R: V _{CC} = 3.0V; MAX70_S/T: V _{CC} = 3.3V		140	200	280	ms
		V _{CC} = 5.0V			200		
RESET Output Voltage (MAX70_R/S/T)	V _{OH}	V _{RST} (max) < V _{CC} < 3.6V	I _{SOURCE} = 500μA	0.8 x V _{CC}		V	
	V _{OL}		I _{SINK} = 1.2mA	0.3			
	V _{OH}	4.5V < V _{CC} < 5.5V	I _{SOURCE} = 800μA	V _{CC} - 1.5			
	V _{OL}		I _{SINK} = 3.2mA	0.4			
	V _{OL}	MAX70_C: V _{CC} = 1.0V, I _{SINK} = 50μA		0.3			
		MAX70_E/M: V _{CC} = 1.2V, I _{SINK} = 100μA		0.3			
RESET Output Voltage (MAX706P)	V _{OH}	V _{RST} (max) < V _{CC} < 3.6V	I _{SOURCE} = 215μA	V _{CC} - 0.6		V	
	V _{OL}		I _{SINK} = 1.2mA	0.3			
	V _{OH}	4.5V < V _{CC} < 5.5V	I _{SOURCE} = 800μA	V _{CC} - 1.5			
	V _{OL}		I _{SINK} = 3.2mA	0.4			

+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

ELECTRICAL CHARACTERISTICS (continued)

(MAX70_P/R: $V_{CC} = 2.70V$ to $5.5V$, MAX70_S: $V_{CC} = 3.00V$ to $5.5V$, MAX70_T: $V_{CC} = 3.15V$ to $5.5V$, $T_A = T_{MIN}$ to T_{MAX} , unless otherwise noted.)


PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
RESET Output Voltage (MAX708_)	V _{OH}	V _{RST} (max) < V _{CC} < 3.6V	I _{SOURCE} = 500μA	0.8 × V _{CC}			V
	V _{OL}		I _{SINK} = 500μA	0.3			
	V _{OH}	4.5V < V _{CC} < 5.5V	I _{SOURCE} = 800μA	V _{CC} - 1.5			
	V _{OL}		I _{SINK} = 1.2mA	0.4			
Watchdog Timeout Period (MAX706_)	t _{WD}	MAX70_P/R: V _{CC} = 3.0V; MAX70_S/T: V _{CC} = 3.3V		1.0	1.6	2.25	sec
WDI Pulse Width (MAX706_)	t _{WP}	V _{IL} = 0.4V, V _{IH} = 0.8 × V _{CC}	V _{RST} (max) < V _{CC} < 3.6V	100			ns
			4.5V < V _{CC} < 5.5V	50			
WDI Input Threshold (MAX706_)	V _{IL}	V _{RST} (max) < V _{CC} < 3.6V	Low	0.6			V
	V _{IH}		High	0.7 × V _{CC}			
	V _{IL}	V _{CC} = 5.0V	Low	0.8			
	V _{IH}		High	3.5			
WDI Input Current (MAX706_)		WDI = 0V or V _{CC}		-1.0	0.02	1.0	μA
WDO Output Voltage (MAX706_)	V _{OH}	V _{RST} (max) < V _{CC} < 3.6V	I _{SOURCE} = 500μA	0.8 × V _{CC}			V
	V _{OL}		I _{SINK} = 500μA	0.3			
	V _{OH}	4.5V < V _{CC} < 5.5V	I _{SOURCE} = 800μA	V _{CC} - 1.5			
	V _{OL}		I _{SINK} = 1.2mA	0.4			
MR Pull-Up Current		MR = 0V	V _{RST} (max) < V _{CC} < 3.6V	25	70	250	μA
			4.5V < V _{CC} < 5.5V	100	250	600	
MR Pulse Width	t _{MR}	V _{RST} (max) < V _{CC} < 3.6V		500			ns
		4.5V < V _{CC} < 5.5V		150			
MR Input Threshold	V _{IL}	V _{RST} (max) < V _{CC} < 3.6V	Low	0.6			V
	V _{IH}		High	0.7 × V _{CC}			
	V _{IL}	4.5V < V _{CC} < 5.5V	Low	0.8			
	V _{IH}		High	2.0			
MR to Reset Out Delay (Note 2)	t _{MD}	V _{RST} (max) < V _{CC} < 3.6V		750			ns
		4.5V < V _{CC} < 5.5V		250			
PFI Input Threshold		MAX70_P/R: V _{CC} = 3.0V; MAX70_S/T: V _{CC} = 3.3V, PFI falling		1.20	1.25	1.30	V
PFI Input Current				-25	0.01	25	nA
PFO Output Voltage	V _{OH}	V _{RST} (max) < V _{CC} < 3.6V	I _{SOURCE} = 500μA	0.8 × V _{CC}			V
	V _{OL}		I _{SINK} = 1.2mA	0.3			
	V _{OH}	4.5V < V _{CC} < 5.5V	I _{SOURCE} = 800μA	V _{CC} - 1.5			
	V _{OL}		I _{SINK} = 3.2mA	0.4			

Note 2: Applies to both \overline{RESET} in the MAX70_R/S/T, and \overline{RESET} in the MAX706P and MAX708R/S/T.


+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

Typical Operating Characteristics


**RESET, $\overline{\text{RESET}}$ OUTPUT VOLTAGES
vs. SUPPLY VOLTAGE
(RESET OUTPUTS AND RESET THRESHOLDS
SHOWN FOR MAX708T, $T_A = +25^\circ\text{C}$)**




RESET, $\overline{\text{RESET}}$ RESPONSE TIMES




**POWER-FAIL COMPARATOR
ASSERTION RESPONSE TIME**




**POWER-FAIL COMPARATOR
DEASSERTION RESPONSE TIME**



**RESET, $\overline{\text{RESET}}$
RISE AND FALL TIMES
(RESET ASSERTED)**



**RESET, $\overline{\text{RESET}}$
RISE AND FALL TIMES
(RESET DEASSERTED)**



+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

Pin Description

MAX706P/R/S/T, MAX708R/S/T

PIN						NAME	FUNCTION
MAX706P		MAX706R/S/T		MAX708R/S/T			
DIP/SO	μMAX	DIP/SO	μMAX	DIP/SO	μMAX		
1	3	1	3	1	3	MR	Manual-Reset Input. When pulled below 0.6V, MR triggers a reset pulse. It is TTL/CMOS-compatible when VCC = 5V and can be shorted to ground with a switch. This active-low input has an internal 70μA pull-up current. Leave floating or connect to VCC if not used.
2	4	2	4	2	4	VCC	Supply-Voltage Input
3	5	3	5	3	5	GND	Ground
4	6	4	6	4	6	PFI	Power-Fail Comparator Input. When PFI is less than 1.25V, PFO goes low; otherwise PFO remains high. Connect PFI to GND when not used.
5	7	5	7	5	7	PFO	Power-Fail Output. When PFI is less than 1.25V, PFO goes low and sinks current; otherwise, PFO remains high. Leave unconnected if not used.
6	8	6	8	–	–	WDI	Watchdog Input. A rising or falling edge must occur at WDI within 1.6sec or WDO goes low (Figure 4). The internal watchdog timer is reset to zero when reset is asserted or when a transition occurs at WDI. The watchdog function cannot be disabled.
–	–	–	–	6	8	N.C.	No Connect—not internally connected.
–	–	7	1	7	1	RESET	Active-Low Reset Output. RESET remains low while VCC is below the reset threshold or MR is held low. It remains low for 200ms after the reset condition are terminated (Figure 3).
7	1	–	–	8	2	RESET	Active-High Reset Output. RESET remains high while VCC is below the reset threshold or MR is held low. It remains high for 200ms after the reset conditions are terminated (Figure 3).
8	2	8	2	–	–	WDO	Watchdog Output. WDO goes low when a transition does not occur at WDI within 1.6sec, and remains low until a transition occurs at WDI (indicating the watchdog interrupt has been serviced). WDO also goes low when VCC falls below the reset threshold; however, unlike the reset output signal, WDO goes high as soon as VCC exceeds the reset threshold.

Detailed Description

$\overline{\text{RESET}}$ and RESET Outputs

A microprocessor's (μ P's) reset input starts it in a known state. When the μ P is in an unknown state, it should be held in reset. The MAX706P/R/S/T and MAX708R/S/T assert reset when V_{CC} is low, preventing code execution errors during power-up, power-down or brownout conditions.

On power-up, once V_{CC} reaches 1V, $\overline{\text{RESET}}$ is guaranteed to be a logic low and RESET is guaranteed to be a logic high. As V_{CC} rises, $\overline{\text{RESET}}$ and RESET remain asserted. Once V_{CC} exceeds the reset threshold, the internal timer causes $\overline{\text{RESET}}$ and RESET to be deasserted after a time equal to the reset pulse width, which is typically 200ms (Figure 3). If a power-fail or brownout condition occurs (i.e. V_{CC} drops below the reset threshold), $\overline{\text{RESET}}$ and RESET are asserted. As long as V_{CC} remains below the reset threshold, the internal timer is continually reset, causing the $\overline{\text{RESET}}$ and RESET outputs

to remain asserted. Thus, a brownout condition that interrupts a previously initiated reset pulse causes an additional 200ms delay from the time the latest interruption occurred. On power-down, once V_{CC} drops below the reset threshold, $\overline{\text{RESET}}$ and RESET are guaranteed to be asserted for $V_{CC} \geq 1V$.

The MAX706P provides a RESET signal, the MAX706R/S/T provide a $\overline{\text{RESET}}$ signal, and the MAX708R/S/T provide both RESET and $\overline{\text{RESET}}$.

Watchdog Timer (MAX706P/R/S/T)

The MAX706P/R/S/T watchdog circuit monitors the μ P's activity. If the μ P does not toggle the Watchdog Input (WDI) within 1.6sec, the Watchdog Output (WDO) goes low (Figure 4). If the reset signal is asserted, the watchdog timer will be reset to zero and disabled. As soon as reset is released, the timer starts counting. WDI can detect pulses as narrow as 100ns with a 2.7V supply and 50ns with a 4.5V supply.

MAX706P/R/S/T, MAX708R/S/T



Manual Reset

Power-Fail Comparator

Figure 2. MAX708R/S/T Block Diagram

+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits




Figure 3. RESET, RESET, MR and WDO Timing




Figure 4. MAX706P/R/S/T Watchdog Timing

ble-instrument applications where power can be supplied from either a +3V battery or an AC-DC wall adapter that generates +5V (a +5V supply allows a μ P or a microcontroller to run faster than a +3V supply). With a +3V supply, these ICs consume less power, but output drive capability is reduced, the MR-to-RESET delay time increases, and the MR minimum pulse width increases. The *Electrical Characteristics* table provides specifications for operation with both +3V and +5V supplies.

Ensuring a Valid RESET Output Down to $V_{CC} = 0V$

When V_{CC} falls below 1V, the MAX706R/S/T and MAX708R/S/T RESET output no longer sinks current; it becomes an open circuit. High-impedance, CMOS logic inputs can drift to undetermined voltages if left as open circuits. If a pull-down resistor is added to the RESET pin, as shown in Figure 6, any stray charge or leakage currents will flow to ground, holding RESET low. Resistor




Figure 5. Monitoring Both +3V/+3.3V and +12V




Figure 6. RESET Valid to Ground Circuit

value R1 is not critical, but it should not load RESET and should be small enough to pull RESET and the input it is driving to ground. 100k Ω is suggested for R1.

Adding Hysteresis to the Power-Fail Comparator

Hysteresis adds a noise margin to the power-fail comparator and prevents repeated triggering of PFO when V_{IN} is near the power-fail comparator trip point. Figure 7 shows how to add hysteresis to the power-fail comparator. Select the ratio of R1 and R2 such that PFI sees 1.25V when V_{IN} falls to the desired trip point (V_{TRIP}). Resistor R3 adds hysteresis. R3 will typically be an order of

MAX706P/R/S/T, MAX708R/S/T

+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

magnitude greater than R1 or R2. The current through R1 and R2 should be at least 1 μ A to ensure that the 25nA max PFI input current does not shift the trip point significantly. R3 should be larger than 10k Ω to prevent it from loading down the PFO pin. Capacitor C1 adds noise rejection.

Monitoring a Negative Voltage

The power-fail comparator can be used to monitor a negative supply voltage using the circuit of Figure 8. When the negative supply is valid, PFO is low. When the negative supply voltage drops, PFO goes high. This circuit's accuracy is affected by the PFI threshold tolerance, the VCC voltage, and resistors R1 and R2.




Figure 7. Adding Hysteresis to the Power-Fail Comparator








Figure 8. Monitoring a Negative Voltage

+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

Typical Operating Circuits (continued)



Pin Configurations (continued)



() ARE FOR MAX706P ONLY.

Chip Information

TRANSISTOR COUNT: 572

MAX706P/R/S/T, MAX708R/S/T

+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

MAX706P/R/S/T, MAX708R/S/T

Ordering Information (continued)

PART	TEMP RANGE	PIN-PACKAGE
MAX706PEUA	-40°C to +85°C	8 μ MAX
MAX706PMJA	-55°C to +125°C	8 Cerdip*
MAX706RCPA	0°C to +70°C	8 Plastic Dip
MAX706RCSA	0°C to +70°C	8 SO
MAX706RCUA	0°C to +70°C	8 μ MAX
MAX706REPA	-40°C to +85°C	8 Plastic Dip
MAX706RESA	-40°C to +85°C	8 SO
MAX706REUA	-40°C to +85°C	8 μ MAX
MAX706RMJA	-55°C to +125°C	8 Cerdip*
MAX706SCPA	0°C to +70°C	8 Plastic Dip
MAX706SCSA	0°C to +70°C	8 SO
MAX706SCUA	0°C to +70°C	8 μ MAX
MAX706SEPA	-40°C to +85°C	8 Plastic Dip
MAX706SESA	-40°C to +85°C	8 SO
MAX706SEUA	-40°C to +85°C	8 μ MAX
MAX706SMJA	-55°C to +125°C	8 Cerdip*
MAX706TCPA	0°C to +70°C	8 Plastic Dip
MAX706TCSA	0°C to +70°C	8 SO
MAX706TCUA	0°C to +70°C	8 μ MAX
MAX706TEPA	-40°C to +85°C	8 Plastic Dip
MAX706TESA	-40°C to +85°C	8 SO
MAX706TEUA	-40°C to +85°C	8 μ MAX
MAX706TMJA	-55°C to +125°C	8 Cerdip*



PART	TEMP RANGE	PIN-PACKAGE
MAX708RCPA	0°C to +70°C	10 Plastic Dip
MAX708RCSA	0°C to +70°C	8 SO
MAX708RCUA	0°C to +70°C	8 μ MAX
MAX708REPA	-40°C to +85°C	8 Plastic Dip
MAX708RESA	-40°C to +85°C	8 SO
MAX708REUA	-40°C to +85°C	8 μ MAX
MAX708RMJA	-55°C to +125°C	8 Cerdip*
MAX708SCPA	0°C to +70°C	8 Plastic Dip
MAX708SCSA	0°C to +70°C	8 SO
MAX708SCUA	0°C to +70°C	8 μ MAX
MAX708SEPA	-40°C to +85°C	8 Plastic Dip
MAX708SESA	-40°C to +85°C	8 SO
MAX708SEUA	-40°C to +85°C	8 μ MAX
MAX708SMJA	-55°C to +125°C	8 Cerdip*
MAX708TCPA	0°C to +70°C	8 Plastic Dip
MAX708TCSA	0°C to +70°C	8 SO
MAX708TCUA	0°C to +70°C	8 μ MAX
MAX708TEPA	-40°C to +85°C	8 Plastic Dip
MAX708TESA	-40°C to +85°C	8 SO
MAX708TEUA	-40°C to +85°C	8 μ MAX
MAX708TMJA	-55°C to +125°C	8 Cerdip*

* Contact factory for availability and processing to MIL-STD-883.

+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

Package Information

The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information go to www.maxim-ic.com/packages.)




MAX706P/R/S/T, MAX708R/S/T

+3V Voltage Monitoring, Low-Cost, μ P Supervisory Circuits

Package Information (continued)

The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information go to www.maxim-ic.com/packages.)



Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.