



MAX11850/MAX11851 Evaluation Systems

General Description

The MAX11850/MAX11851 evaluation systems (EV systems) demonstrate the low-power projected capacitance touch-sensor controller, which targets power-sensitive applications such as handheld devices. The EV systems include built-in control firmware and a Windows® graphical user interface (GUI) to exercise some of the features of the MAX11850/MAX11851.

Each EV system is a multiboard system offered with or without haptics and consists of a MAXQ2000 USB touch interface board (UTIB2), a MAX11850 or MAX11851 daughter board, and a MAX11835 daughter board (haptic versions only).

Features

- ◆ Convenient USB Interface
- ◆ USB Power and On-Board LDOs Eliminate Need for External Power Supply
- ◆ JTAG Ports Included for Programming/Debugging of the MAXQ2000 and MAX11850/MAX11851
- ◆ Densitron Touch Screen (Included with EV System)
- ◆ All Components Mounted on a Plexiglas Base for Ease of Handling
- ◆ Allows Evaluation of Single-Touch and Dual-Touch Modes
- ◆ Can Be Adapted to Work with Other Touch Panels (Not Included with EV System)
- ◆ Demonstrates Single-Layer Piezo Haptics Using MAX11835 Daughter Board (Optional)

Ordering Information/Selector Guide

PART	TYPE	PC INTERFACE	INTERFACE TYPE
MAX11850HTEVS+	EV System (with haptics)	USB	Windows
MAX11850TEVS+	EV System (without haptics)	USB	Windows
MAX11851HTEVS+	EV System (with haptics)	USB	Windows
MAX11851TEVS+	EV System (without haptics)	USB	Windows

+Denotes lead(Pb)-free and RoHS compliant.

EV System Contents List

QTY	DESCRIPTION
1	CD-ROM containing USB driver, quick guide, GUI software for Windows, and PCB schematic and layout files
1	USB touch interface board (MAXQ2000 UTIB2 board)
1	Touch-screen driver daughter board (MAX11850 or MAX11851) with a connector to plug in to the UTIB2 board
1	Piezo driver MAX11835 daughter board with a connector to plug in to the UTIB2 board (included with haptic versions only)
1	Densitron 4.3in touch panel (Densitron DTS413-0430-1FX-000; Densitron Corporation, 951-284-7600) and a flex cable to connect to the MAX11850 or MAX11851 daughter board
1	Coaxial cable to connect the MAX11835 daughter board to the piezo drivers (included with haptic versions only)
1	Mini USB cable

Windows is a registered trademark of Microsoft Corp.



MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




Figure 1. MAX11850/MAX11851 Evaluation System (Shown with Haptics)

MAX11850/MAX11851 Evaluation Systems

Component Lists

MAXQ2000 UTIB2 Board

DESIGNATION	QTY	DESCRIPTION
C1, C4, C5, C6, C8, C10, C14, C17, C18, C21, C22, C25, C26, C36, C37	15	0.1 μ F -20/+80%, 16V ceramic capacitors (0603) Murata GRM188F51C104ZA01D
C2, C7	2	22pF \pm 5%, 50V ceramic capacitors (0603) Murata GRM1885C1H220JA01D
C3, C11, C15, C19, C27, C28, C33, C34	8	1 μ F -20/+80%, 16V ceramic capacitors (0603) Murata GRM188F51C105ZA01D
C9, C12, C16, C20, C30, C31	6	10 μ F \pm 20%, 6.3V ceramic capacitors (0603) Murata GRM188R60J106ME47D
C13	1	33nF \pm 10%, 16V ceramic capacitor (0603) Murata GRM188R71C333KA01D
C23, C24	2	10pF \pm 5%, 50V ceramic capacitors (0603) Murata GRM1885C1H100JA01D
EN1B, EN2B, U2-PIN1, U2-PIN2	4	2-pin headers, 100 mil
FB1, FB3, FB4	3	100 μ H \pm 10% ferrite beads (1206) TDK FL3215T-101K
FB2	1	0 Ω resistor (1206) Vishay CRCW12060000Z0EA
GND1, GND5	2	Pad loops, #20 wire
GND2, GND3, GND4	3	Single-pin test points
J1, J4, J6, J8, J9, J10, J18, J19, J25, J26	10	2-pin headers, 100 mil Sullins PBC02SABN
J2, J5, J11, J12, J14, J16, J17	7	3-pin headers, 100 mil Sullins PBC03SABN
J3, J13	2	10-pin headers, 100 mil Sullins PBC05DAAN

DESIGNATION	QTY	DESCRIPTION
J7	1	USB-Mini-5P receptacle Hirose UX60-MB-5ST
J15	1	8-pin header, 100 mil Sullins PBC08SABN
J22	1	20-pin header, 100 mil
J23, J24	2	21-pin female connectors Hirose DF9-21S-1V(32)
LED1, LED2, LED3	3	SMD RGB LEDs (0805) Lite-On LTST-C171KYKT
R1	1	470 Ω resistor (0805) Vishay CRCW0805470RJNEA
R2, R37	2	590k Ω \pm 5% resistors (0805) Vishay CRCW0805590KJNEA
R3, R25	2	51k Ω \pm 5% resistors (0805) Vishay CRCW080551KJNEA
R4	1	2.2k Ω \pm 5% resistor (0805) Vishay CRCW08052K20JNEA
R5, R8, R10, R11, R13	0	Not installed, 0 Ω resistors (0603)
R6	1	61.9k Ω \pm 1% resistor (0805) Vishay CRCW080561K9FKEA
R7	1	10k Ω \pm 5% resistor (0805) Vishay CRCW080510K0JNEA
R9, R39	2	196k Ω \pm 5% resistors (0805) Vishay CRCW0805196KJNEA
R12, R16, R18	3	215 Ω resistors (0805) Vishay CRCW0805215RJNEA
R14, R15, R22, R42, R44, R45, R46	7	100k Ω \pm 5% resistors (0805) Vishay CRCW0805100KJNEA
R17	1	1.5k Ω \pm 5% resistor (0805) Vishay CRCW08051K50JNEA
R19, R20, R21, R24, R26, R27, R47, R51	8	4.7k Ω \pm 5% resistors (0805) Vishay CRCW08054K70JNEA

Evaluate: MAX11850/MAX11851

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851

Component Lists (continued)

MAXQ2000 UTIB2 Board (continued)

DESIGNATION	QTY	DESCRIPTION
R23	1	169kΩ ±5% resistor (0805) Vishay CRCW0805169KJNEA
R28	1	10kΩ ±5% resistor (0603) Vishay CRCW080510K0FKEA
R30, R31	2	3.3kΩ ±5% resistors (0805) Vishay CRCW08053K30JNEA
R32	0	Not installed, resistor (0805)
R34	1	316kΩ ±5% resistor (0805) Vishay CRCW0805316KJNEA
R41	1	47kΩ ±5% resistor (0805) Vishay CRCW080547K0JNEA
U1	1	2kB EEPROM (8 SO) Atmel AT93C56A
U2	1	UART, 7mm x 7mm (32 TQFP) FTDI FT232BL
U3, U4, U10, U11	4	Adjustable LDO linear regulators (5 SC70) Maxim MAX8512EXK-T+
U5, U13	2	Quad-level translators (12 TQFN-EP*) Maxim MAX3395EETC+

DESIGNATION	QTY	DESCRIPTION
U6	1	Fixed 2.5V LDO linear regulator (5 SC70) Maxim MAX8511EXK25-T+
U7	1	Octal-level translator (20 TSSOP) Maxim MAX3001EEUP+
U8	1	16-bit microcontroller (68 QFN-EP*) Maxim MAXQ2000-RAX+
Y1	1	6MHz crystal (HCM49) ECS ECS-60-20-5G3XDS-TR
Y2	0	Not installed, oscillator
Y3	1	16MHz crystal (HCM49) ECS Inc. ECS-160-20-5PDN-TR
Y4	0	Not installed, crystal Citizen CMR200T
—	1	PCB: USB Touch Interface Board 2

*EP = Exposed pad.

MAX11851 Daughter Board

DESIGNATION	QTY	DESCRIPTION
C1, C2, C4, C6	4	1μF ±10% ceramic capacitors (0603)
J1	1	36-position Molex connector Molex 0541043631
J2	1	21-position male connector Hirose DF9-21P-1V(32)-Male

DESIGNATION	QTY	DESCRIPTION
J3–J6	4	Through hole for legs, stuff with 0.025in square header post
U1	1	Low-power touch-sensor controller (40 TQFN) Maxim MAX11851ETL+
—	1	PCB: FP21 EVALUATION KIT

MAX11850/MAX11851 Evaluation Systems

Component Lists (continued)

MAX11850 Daughter Board

DESIGNATION	QTY	DESCRIPTION
C1, C2, C4, C6	4	1 μ F \pm 10% ceramic capacitors (0603)
J1	1	36-position Molex connector Molex 0541043631
J2	1	21-position male connector Hirose DF9-21P-1V(32)-Male

DESIGNATION	QTY	DESCRIPTION
J3–J6	4	Through hole for legs, stuff with 0.025in square header post
U1	1	Low-power touch-sensor controller (48 TQFN) Maxim MAX11850ETM+
—	1	PCB: MAX11850 EVALUATION KIT

MAX11835 Daughter Board

DESIGNATION	QTY	DESCRIPTION
ADD0, ADD1, DIS, IRQB, RESETB, SCL, SDA, TRIGB	0	Not installed, test points
CF1	1	10 μ F X54 ceramic capacitor (0805) Murata GRM21BF50J106ZE01L
CF2	1	47nF, 200V ceramic capacitor (0805) KEMET C0805C473K2RACTU
CF3, CF4	2	4.7 μ F, 10V X5R ceramic capacitors (0402) KEMET C0402C475MPACTU
CL	0	Not installed, SMD ceramic capacitor (0805)
C1	0	Not installed, SMD ceramic capacitor (0603)
D1	1	200V diode
FP03	1	Haptic piezo controller (25 WLP) Maxim MAX11835
J1	1	2-pin header, 0.1in pitch
J2	1	21-position connector Hirose DF9-21P-1V(32)
J3, J5, J7	3	3-pin headers, 0.1in pitch
J4	0	Not installed, 20-position connector
J6	1	4-pin header, 0.1in pitch

DESIGNATION	QTY	DESCRIPTION
LED1	1	Red SMD LED, 1.6mm x 0.8mm
Q1	1	n-channel MOSFET (Hex DIP) PD = 1W, ID = 0.6A, VDSS = 200V, VGS = \pm 20V, VSD = 2V, RDS(ON) = 1 Ω
R1	1	2M Ω \pm 1%, 250V resistor (0805)
R2	1	27k Ω SMD resistor (0402)
R3, R8, R9, R11	4	0 Ω SMD resistors (0805)
R4, R6	2	4.7k Ω SMD resistors (0402)
R5	1	20 Ω SMD resistor (0603)
R7	1	220 Ω SMD resistor (0402)
R10	1	1 Ω SMD resistor (0805)
R12	0	Not installed, SMD resistor (0402)
R13	1	0 Ω SMD resistor (0402)
R14	1	5k Ω resistor (0603)
R17, R18	2	49.9 Ω SMD resistors (0603)
R19, R20	0	Not installed, SMD resistors (0603)
T1	1	Boost transformer
T4, TP1–TP5, TT1, TT5, VBATT_, VOUT	0	Not installed, test points
U1	1	3.5mm stereo audio jack
X1–X4	4	Empty holes, leave open
—	1	PCB: MAX11835 EVALUATION KIT

Evaluate: MAX11850/MAX11851

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851

Table 1. UTIB2 Ports

PORT	DESCRIPTION
J3	JTAG port for programming of the J24 daughter card
J7	USB port provides power to the EV systems and communication to a PC
J13	JTAG port for programming the MAXQ2000
J15	Access to the MAXQ2000 GPIOs
J22	Access to the MAXQ2000 ports
J23	Connector to plug in the MAX11835 daughter board (includes 3V supply pin and independent reset line)
J24	Connector to plug in the MAX11850 daughter board (includes 3V and 1.8V supplies and independent reset line)

Table 2. UTIB2 Default Jumper Settings

JUMPER	SHUNT POSITION	STATUS
J1	1-2	Closed
J3	—	JTAG connector for the MAX11850
J4	1-2	Open
J5	1-2	Open
J6	1-2	Open
J8	1-2	Open
J9	1-2	Open
J10	1-2	Open
J12	2-3	Closed
J13	—	JTAG connector for the MAXQ2000
J14	2-3	Closed

JUMPER	SHUNT POSITION	STATUS
J15	—	MAXQ2000 GPIO pins
J16	1-2	Closed
J17	1-2	Closed
J18	1-2	—
J19	1-2	Closed
J20	—	Open
J21	Open	Open
J22	Open	Open
J23	—	Connector to plug in the MAX11835 daughter board
J24	—	Connector to plug in the MAX11850 daughter board

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851

Note: Jumper Settings For J12 & J14
For SPI Operation, Jumper Pins 1 & 2
For I2C Operation, Jumper Pins 2 & 3




Figure 2a. UTIB2 Schematic—Main (Sheet 1 of 3)

MAX11850/MAX11851 Evaluation Systems




Figure 2b. UTIB2 Schematic—Mini USB (Sheet 2 of 3)

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




Figure 2c. UTIB2 Schematic—Supply (Sheet 3 of 3)

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




Figure 3. MAX11851 Daughter Board Schematic

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




Figure 4. MAX11850 Daughter Board Schematic

MAX11850/MAX11851 Evaluation Systems




Figure 5. MAX11835 Daughter Board Schematic

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




Figure 6. UTIB2 Component Placement Guide—Silkscreen




Figure 7. UTIB2 Component Placement Guide—Top Assembly

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




Figure 8. UTIB2 PCB Layout—Top Layer




Figure 9. UTIB2 PCB Layout—Layer 2

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




Figure 10. UTIB2 PCB Layout—Layer 3




Figure 11. UTIB2 Component Placement Guide—Bottom Assembly

MAX11850/MAX11851 Evaluation Systems




Figure 12. MAX11851 Component Placement Guide—Silkscreen




Figure 13. MAX11851 Component Placement Guide—Top Assembly




Figure 14. MAX11851 PCB Layout—Top Layer

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




Figure 15. MAX11851 PCB Layout—Layer 2




Figure 16. MAX11851 PCB Layout—Layer 3






Figure 17. MAX11851 PCB Layout—Bottom Layer

MAX11850/MAX11851 Evaluation Systems




1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White

Figure 18. MAX11851 Component Placement Guide—Bottom Assembly



1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White

Figure 19. MAX11851 Component Placement Guide—Silkscreen




1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White

Figure 20. MAX11851 Component Placement Guide—Top Assembly


MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White

Figure 21. MAX11850 PCB Layout—Top Layer



1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White


Figure 22. MAX11850 PCB Layout—Layer 2



1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White


Figure 23. MAX11850 PCB Layout—Layer 3

MAX11850/MAX11851 Evaluation Systems




1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White

Figure 24. MAX11850 PCB Layout—Bottom Layer



1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White

Figure 25. MAX11850 Component Placement Guide—Bottom Assembly




1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White
6. All vias on MAX11835 need to be filled

Figure 26. MAX11835 Component Placement Guide—Silkscreen


MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851



1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White
6. All vias on MAX11835 need to be filled

Figure 27. MAX11835 Component Placement Guide—Top Assembly



1. Board Material, FR4
2. Board Thickness, 0.062"
3. Gold Imersion
4. Soldermask Color, Blue
5. Silkscreen Color, White
6. All vias on MAX11835 need to be filled

Figure 28. MAX11835 PCB Layout—Top Layer

MAX11850/MAX11851 Evaluation Systems




Figure 29. MAX11835 PCB Layout—Layer 2




Figure 30. MAX11835 PCB Layout—Layer 3

MAX11850/MAX11851 Evaluation Systems

Evaluate: MAX11850/MAX11851




Figure 31. MAX11835 PCB Layout—Bottom Layer




Figure 32. MAX11835 Component Placement Guide—Bottom Assembly

MAX11850/MAX11851 Evaluation Kit

Revision History

REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
0	6/10	Initial release	—

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

24 _____ **Maxim Integrated Products, 120 San Gabriel Drive, Sunnyvale, CA 94086 408-737-7600**