

DESCRIPTION

The MP20045 is a low-dropout linear regulator supplies up to 1A current with 140mV dropout voltage. The output voltage is set externally which ranges from 1.5V to 5V by operating from +2.5V to +5.5V input or can be preset internally from 1.5V to 5V.

An internal PMOS pass element is used to allow a low 110µA ground current, making the MP20045 suitable for battery-power devices. Other features include low-power shutdown, short-circuit and thermal protection. The MP20045 is available in 8-pin QFN (3mm x 3mm) and SOIC8E packages.

FEATURES


- Up to 1A Output Current
- Low 140mV Dropout at 1A
- Low 110µA Ground Current
- Fixed Output Versions Ranging from 1.5V to 5V and Adjustable Versions
- Open Drain Power-Good Status Output
- 13µV_{RMS} Low Noise Output
- 56dB PSRR at 1kHz
- Current Limiting and Thermal Protection
- 3mm×3mm QFN8 and SOIC8E Packages

APPLICATIONS


- Notebook Computers
- Cordless Telephones
- Cellular Phones
- Modems
- Hand-Held Instruments
- PDA and Palmtop Computers

"MPS" and "The Future of Analog IC Technology" are Registered Trademarks of Monolithic Power Systems, Inc.

TYPICAL APPLICATION



Fixed Version



Adjustable Version

ORDERING INFORMATION

Part Number*	Output Voltage	Package	Top Marking	Free Air Temperature (T _A)
MP20045DQ**	Adjustable	QFN8 (3mm x 3mm)	8K	-40°C to +85°C
MP20045DQ-15**	1.5V	QFN8 (3mm x 3mm)	2V	
MP20045DQ-18**	1.8V	QFN8 (3mm x 3mm)	3V	
MP20045DQ-25**	2.5V	QFN8 (3mm x 3mm)	9Z	
MP20045DQ-33**	3.3V	QFN8 (3mm x 3mm)	2S	
MP20045DN**	Adjustable	SOIC8E	M20045DN	
MP20045DN-15**	1.5V	SOIC8E	20045-15	
MP20045DN-18**	1.8V	SOIC8E	20045-18	
MP20045DN-25**	2.5V	SOIC8E	20045-25	
MP20045DN-33**	3.3V	SOIC8E	20045-33	

* For fixed output voltage versions between 1.5V and 5V, add suffix –XX (e.g. MP20045DQ-33, MP20045DN-33 are the 3.3V fixed output). Contact factory for availability.

** For Tape & Reel, add suffix –Z (e.g. MP20045DQ–Z, MP20045DN–Z);
For RoHS compliant packaging, add suffix –LF (e.g. MP20045DQ–LF–Z, MP20045DN–LF–Z).

PACKAGE REFERENCE

TOP VIEW QFN8 (3mm x 3mm)	TOP VIEW SOIC8E
---	---

ABSOLUTE MAXIMUM RATINGS ⁽¹⁾

VIN, EN, PG, FB to GND	-0.3V to +6V
OUT to GND	-0.5V to V _{IN} + 0.5V
Continuous Power Dissipation (T _A =+25°C) ⁽²⁾	
QFN8 (3x3)	2.0W
SOIC8E	2.0W
Free Air Temperature (T _A).....	-40°C to 85°C
Storage Temperature Range	-65°C to 150°C
Lead Temperature (Soldering, 10sec).....	260°C

ESD Susceptibility

HBM (Human Body Mode).....	2kV
MM (Machine Mode).....	200V

Recommended Operating Conditions ⁽³⁾

Supply Input Voltage.....	2.5V to 5.5V
Enable Input Voltage	0V to 5.5V
Operating Junct. Temp (T _J).....	-40°C to +125°C

Thermal Resistance ⁽⁴⁾

	θ_{JA}	θ_{JC}
QFN8 (3x3)	50	12 ... °C/W
SOIC8E	50	10 ... °C/W

Notes:

- 1) Exceeding these ratings may damage the device.
- 2) The maximum allowable power dissipation is a function of the maximum junction temperature T_J(MAX), the junction-to-ambient thermal resistance θ_{JA} , and the ambient temperature T_A. The maximum allowable continuous power dissipation at any ambient temperature is calculated by P_D(MAX)=(T_J(MAX)-T_A)/ θ_{JA} . Exceeding the maximum allowable power dissipation will cause excessive die temperature, and the regulator will go into thermal shutdown. Internal thermal shutdown circuitry protects the device from permanent damage.
- 3) The device is not guaranteed to function outside of its operating conditions.
- 4) Measured on JESD51-7 4-layer board.

ELECTRICAL CHARACTERISTICS

$V_{IN}=V_{OUT}+0.5V$ or $V_{IN}=2.5V$, $EN=V_{IN}$, Typical values are at $T_A=+25^{\circ}C$, unless otherwise specified

Parameter		Condition		Min	Typ	Max	Units
Input Voltage				2.5		5.5	V
Input Under voltage Lockout		V _{IN} rising		2.0		2.3	V
Hysteresis of UVLO					160		mV
FB Accuracy	Adjustable	I _{OUT} =1mA		-2.5		2.5	%
Output Voltage Accuracy	1.5V	I _{OUT} =1mA, 2.5V<V _{IN} <5.5V		-2.5		2.5	
	1.8V	I _{OUT} =1mA, 2.5V<V _{IN} <5.5V		-2.5		2.5	
	2.5V	I _{OUT} =1mA, 3V<V _{IN} <5.5V		-2.5		2.5	
	3.3V	I _{OUT} =1mA, 3.8V<V _{IN} <5.5V		-2.5		2.5	
Maximum Output Current		Continuous, V _{IN} >=3V		1			A
Short-Circuit Current Limit		V _{OUT} =0, V _{IN} >=3V			1.6		A
In-Regulation Current Limit		V _{OUT} within 4% of normal output voltage V _{IN} =5.5V		1.4	2.2	3.0	A
Ground Current		I _{OUT} =100μA			110		μA
Dropout Voltage ⁽⁵⁾		I _{OUT} =1A			140	280	mV
Line Regulation ⁽⁶⁾		V _{IN} from V _{OUT} +0.5V to 5.5V, I _{OUT} =5mA		-0.15		0.15	%/V
Load Regulation ⁽⁷⁾		I _{OUT} from 1mA to 1A			-0.3		%
Output Voltage Noise		V _{IN} =3.3V, V _{OUT} =2.8V, C _{OUT} =2.2μF, I _{OUT} =100mA, f ranges from 10Hz to 100kHz			13		μV _{RMS}
PSRR		At 1kHz, I _{OUT} =250mA			56		dB
Shutdown Supply Current		V _{IN} =+5.5V			5	16	μA
EN PIN Threshold		EN Logic High		1.5			V
		EN Logic Low				0.4	
EN pin PULL-UP resistor				550k	1.1M		Ω
Thermal Shutdown Temperature		Typical thermal hysteresis =20°C			150		°C
PG	Minimum input voltage	I _{OUT(PG)} =300μA			1.1	1.3	V
	Trip threshold voltage	V _{OUT} decreasing	MP20045	80		86	%V _{OUT}
			MP20045-15				
			MP20045-18				
			MP20045-25				
		MP20045-33	77		83		
	Hysteresis voltage	Measured at V _{OUT}			6		%V _{OUT}
Output low voltage	I _{OUT(PG)} =1mA			0.15	0.4	V	
Leakage current		V _(PG) =5.5V				1	μA

Notes:

5) Dropout Voltage is defined as the input to output differential when the output voltage drops 100mV below its nominal value.

$$6) \text{ Line Regulation} = \frac{V_{OUT[V_{IN(MAX)}]} - V_{OUT[V_{IN(MIN)}]}}{[V_{IN(MAX)} - V_{IN(MIN)}] \times V_{OUT(NOM)}} \times 100(\% / V)$$

$$7) \text{ Load Regulation} = \frac{V_{OUT[I_{OUT(MAX)}]} - V_{OUT[I_{OUT(MIN)}]}}{V_{OUT(NOM)}} \times 100(\%)$$


PIN DESCRIPTION

QFN8 (3X3) Pin #	SOIC8E Pin #	Name	Description
1, 2	7, 8	VIN	Regulator Input. Supply voltage ranges from +2.5V to 5.5V. Bypass with 2.2 μ F capacitor. These pins must be externally connected for proper operation even if they are internally connected.
3, 4	1, 2	VOUT	Regulator output. Bypass with a 2.2 μ F low-ESR capacitor to GND. Connect all the pin together externally.
5	3	FB	Feedback Input. For the adjustable output version, connect FB to the center point of the external resistor divider. The feedback threshold voltage is 1.5V. For the fixed output version, connect FB to the output directly.
6	4	GND Exposed pad	Ground. Connect exposed pad to GND plane for optimal thermal performance.
7	5	PG	Open-drain power-good (PG) output.
8	6	EN	Positive polarity enable (EN) input. Regulator Enable Control Input. Drive EN above 1.5V to turn on the MP20045. Drive EN below 0.4V to turn it off. Do not float the EN pin.


TYPICAL PERFORMANCE CHARACTERISTICS

$V_{IN}=3.3V$, $V_{OUT}=2.8V$, $C_{IN}=C_{OUT}=2.2\mu F$, $T_A=25^\circ C$, unless otherwise noted


Quiescent Current vs. Temperature




Quiescent Current vs. Input Voltage




Dropout Voltage vs. Temperature




Dropout Voltage vs. Output Current




EN threshold vs. Input Voltage




EN threshold vs. Temperature




Current Limit vs. Temperature



Current Limit vs. Input Voltage




Line Regulation




TYPICAL PERFORMANCE CHARACTERISTICS (continued)

$V_{IN}=3.3V$, $V_{OUT}=2.8V$, $C_{IN}=C_{OUT}=2.2\mu F$, $T_A=25^\circ C$, unless otherwise noted


Load Regulation




Output Voltage Accuracy vs. Temperature



PSRR Vs. Frequency



Region of Stable C_{OUT} ESR vs. Output Current




TYPICAL PERFORMANCE CHARACTERISTICS (continued)

$V_{IN}=3.3V$, $V_{OUT}=2.8V$, $C_{IN}=C_{OUT}=2.2\mu F$, $T_A=25^{\circ}C$, unless otherwise noted


Input Power Start Up

$I_{OUT}=1A$, with Resistor Load




Input Power Shutdown

$I_{OUT}=1A$, with Resistor Load




EN Start Up

$I_{OUT}=1A$, with Resistor Load




EN Shutdown

$I_{OUT}=1A$, with Resistor Load




Line Transient

$V_{IN}=3.3V$ to $4.3V$, $I_{OUT}=100mA$, with Resistor Load




Line Transient

$V_{IN}=3.3V$ to $4.3V$, $I_{OUT}=1A$, with Resistor Load




Load Transient


$I_{OUT}=50mA$ to $1A$, with Resistor Load



Power Good Status




Over Current Protection Entry




TYPICAL PERFORMANCE CHARACTERISTICS (*continued*)

$V_{IN}=3.3V$, $V_{OUT}=2.8V$, $C_{IN}=C_{OUT}=2.2\mu F$, $T_A=25^{\circ}C$, unless otherwise noted


**Over Current Protection
Steady State**
No Load



**Over Current Protection
Recovery**
No Load



Current Limit



APPLICATION INFORMATION

Setting the Output Voltage

The output voltage of MP20045 can be set externally which ranges from 1.5V to 5V by operating from +2.5V to +5.5V input or preset internally at 1.5V, 1.8V, 2.5V, 3.3V, 5V. For the adjustable version, the output voltage is set by using a resistive voltage divider from the output voltage to FB pin. The voltage divider divides the output voltage down to the feedback voltage by the ratio:

$$V_{FB} = V_{OUT} \frac{R2}{R1 + R2}$$

Where V_{FB} is the feedback threshold voltage ($V_{FB} = 1.5V$), and V_{OUT} is the output voltage. Thus the output voltage is:

$$V_{OUT} = 1.5 \times \frac{R1 + R2}{R2}$$

$R2$ can be as high as 100k Ω , but a typical value is 10k Ω . Using that value, $R1$ is determined by:

$$R1 = R2 \times \left(\frac{V_{OUT} - V_{FB}}{V_{FB}} \right)$$

For example, for a 2.8V output voltage, $R2$ is 10k Ω , and $R1$ is 8.66k Ω . You can select a standard 8.66k Ω ($\pm 1\%$) resistor for $R1$.

Power Dissipation

The power dissipation for any package depends on the thermal resistance of the case and circuit board, the temperature difference between the junction and ambient air, and the rate of air flow. The power dissipation across the device can be represented by the equation:

$$P = (V_{IN} - V_{OUT}) \times I_{OUT}$$

The allowable power dissipation can be calculated using the following equation:

$$P_{(MAX)} = (T_{Junction} - T_{Ambient}) / \theta_{JA}$$

Where $(T_{Junction} - T_{Ambient})$ is the temperature difference between the junction and the surrounding environment, θ_{JA} is the thermal resistance from the junction to the ambient environment. Connecting the GND pin of MP20045 to ground using a large pad or ground plane helps to channel heat away.

Output Capacitor Selection

The MP20045 is designed specifically to work with very low ESR ceramic output capacitor in space-saving and performance consideration. A 2.2 μF ceramic capacitor with ESR lower than 0.9 Ω is suitable for the MP20045 application circuit. Output capacitor of larger values will help to improve load transient response and reduce noise with the drawback of increased size.






Figure 2—Relationship between ESR and LDO Stability

PACKAGE INFORMATION


SOIC8E



TOP VIEW




BOTTOM VIEW




FRONT VIEW


SEE DETAIL "A"



SIDE VIEW



RECOMMENDED LAND PATTERN




DETAIL "A"


NOTE:

- 1) CONTROL DIMENSION IS IN INCHES. DIMENSION IN BRACKET IS IN MILLIMETERS.
- 2) PACKAGE LENGTH DOES NOT INCLUDE MOLD FLASH, PROTRUSIONS OR GATE BURRS.
- 3) PACKAGE WIDTH DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSIONS.
- 4) LEAD COPLANARITY (BOTTOM OF LEADS AFTER FORMING) SHALL BE 0.004" INCHES MAX.
- 5) DRAWING CONFORMS TO JEDEC MS-012, VARIATION BA.
- 6) DRAWING IS NOT TO SCALE.


QFN8 (3mm×3mm)



TOP VIEW




BOTTOM VIEW




SIDE VIEW


PIN 1 ID OPTION A
0.30x45° TYP.



PIN 1 ID OPTION B
R0.20 TYP.



DETAIL A



RECOMMENDED LAND PATTERN

NOTE:

- 1) ALL DIMENSIONS ARE IN MILLIMETERS.
- 2) EXPOSED PADDLE SIZE DOES NOT INCLUDE MOLD FLASH.
- 3) LEAD COPLANARITY SHALL BE 0.10 MILLIMETER MAX.
- 4) DRAWING CONFORMS TO JEDEC MO-229, VARIATION VEEC-2.
- 5) DRAWING IS NOT TO SCALE.

NOTICE: The information in this document is subject to change without notice. Please contact MPS for current specifications. Users should warrant and guarantee that third party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Monolithic Power Systems (MPS):

[MP20045DN-15-LF](#) [MP20045DN-15-LF-Z](#) [MP20045DN-18-LF](#) [MP20045DN-18-LF-Z](#) [MP20045DN-25-LF](#)
[MP20045DN-25-LF-Z](#) [MP20045DN-33-LF](#) [MP20045DN-33-LF-Z](#) [MP20045DN-LF](#) [MP20045DN-LF-Z](#) [MP20045DQ-](#)
[15-LF-P](#) [MP20045DQ-15-LF-Z](#) [MP20045DQ-18-LF-P](#) [MP20045DQ-18-LF-Z](#) [MP20045DQ-25-LF-P](#) [MP20045DQ-25-](#)
[LF-Z](#) [MP20045DQ-33-LF-P](#) [MP20045DQ-33-LF-Z](#) [MP20045DQ-LF-P](#) [MP20045DQ-LF-Z](#)