

DESCRIPTION

The MP8102 is a rail-to-rail output, operational amplifier in a TSOT-23 package. This amplifier provides 600KHz bandwidth while consuming an incredibly low 7.5 μ A of supply current. The MP8102 can operate with a single supply voltage as low as 1.8V.

FEATURES


- Single Supply Operation: 1.8V to 5.5V
- TSOT23-5 Package
- 600KHz –3dB Bandwidth
- 7.5 μ A Supply Current
- Rail-to-Rail Output
- Unity-Gain Stable
- Input Common Mode to Ground
- Drives Up to 1000pF of Capacitive Loads

APPLICATIONS


- Portable Equipment
- PDAs
- Pagers
- Cordless Phones
- Handheld GPS
- Consumer Electronics

"MPS" and "The Future of Analog IC Technology" are Registered Trademarks of Monolithic Power Systems, Inc.

TYPICAL APPLICATION



PACKAGE REFERENCE



* For Tape & Reel, add suffix –Z (eg. MP8102DJ–Z)
 For RoHS compliant packaging, add suffix –LF (eg.
 MP8102DJ–LF–Z)

ABSOLUTE MAXIMUM RATINGS ⁽¹⁾

Supply Voltage (V+ to V-) +6.0V
 Differential Input Voltage ($V_{IN+} - V_{IN-}$) +6.0V
 Input Voltage ($V_{IN+} - V_{IN-}$).. $V_{IN+} + 0.3V$, $V_{IN-} - 0.3V$

Recommended Operating Conditions ⁽²⁾

Supply Voltage +1.8V to +5.5V
 Operating Temperature –40°C to +85°C

Thermal Resistance ⁽³⁾

θ_{JA} θ_{JC}
 TSOT23-5 220 ... 110.. °C/W

Notes:

- 1) Exceeding these ratings may damage the device.
- 2) The device is not guaranteed to function outside of its operating conditions.
- 3) Measured on approximately 1" square of 1 oz copper.

ELECTRICAL CHARACTERISTICS

$V_+ = +5V$, $V_- = 0V$, $V_{CM} = V_+/2$, $R_L = 10k\Omega$, $T_A = +25^\circ C$, unless otherwise noted.

| Parameter | Symbol | Condition | Min | Typ | Max | Units |
|---------------------------------------|-----------|------------------------------------------------------|-----|--------------|-----|------------------|
| Input Offset Voltage | V_{OS} | | –5 | 1 | +5 | mV |
| Input Offset Voltage Temp Coefficient | | | | 15 | | $\mu V/^\circ C$ |
| Input Bias Current ⁽⁴⁾ | I_B | | | 2 | | pA |
| Input Offset Current ⁽⁴⁾ | I_{OS} | | | 0.2 | | pA |
| Input Voltage Range | V_{CM} | CMRR > 60dB | 0 | | 3.8 | V |
| Common-Mode Rejection Ratio | CMRR | $0 < V_{CM} < 3.5V$ | | 82 | | dB |
| Power Supply Rejection Ratio | PSRR | Supply Voltage change of 1.0V | | 80 | | dB |
| Large Signal Voltage Gain | A_{VOL} | $R_L = 100k\Omega$, $V_{OUT} = 5.0$ Peak to Peak | 60 | 88 | | dB |
| Maximum Output Voltage Swing | V_{OUT} | $R_L = 10k\Omega$ | | $V_+ - 23mV$ | | V |
| Minimum Output Voltage Swing | V_{OUT} | $R_L = 10k\Omega$ | | $V_- + 19mV$ | | V |
| Gain-Bandwidth Product ⁽⁴⁾ | GBW | $R_L = 200k\Omega$, $C_L = 2pF$, $V_{OUT} = 0$ | | 200 | | KHz |
| –3dB Bandwidth ⁽⁴⁾ | BW | $A_V = 1$, $C_L = 2pF$, $R_L = 1M\Omega$ | | 600 | | KHz |
| Slew Rate ⁽⁴⁾ | SR | $A_V = 1$, $C_L = 2pF$, $R_L = 1M\Omega$ | | 0.1 | | V/ μs |
| Short Circuit Current | I_{SC} | Source | | –20 | | mA |
| | | Sink | | 20 | | mA |
| Supply Current | | No Load | | 7.5 | 10 | μA |


Note:

4) Guaranteed by design.

PIN FUNCTIONS

| Pin # | Name | Description |
|-------|------|------------------------------|
| 1 | OUT | Output. |
| 2 | V+ | Supply Voltage. |
| 3 | IN+ | Non-Inverting Input. |
| 4 | IN- | Inverting Input. |
| 5 | V- | Ground or Supply Return Pin. |

TEST CIRCUITS



Notes: Close S3 for positive gain. Input signal to RF(+Av) connector.
The gain $A_v = 1 + R_{FB}/R_{IN}$.
For unity gain, remove R_{IN} and short R_{FB} .
Open S3 for negative gain. Input signal to RF(-Av) connector.
The gain $A_v = -R_{FB}/R_{IN}$.
S1 and S2 are switches for possible resistor and capacitor load connections.

Figure 1—AC Test Circuit

TEST CIRCUITS *(continued)*










Figure 2—Positive Power Supply Rejection Ratio Measurement










TYPICAL PERFORMANCE CHARACTERISTICS

$T_A = +25^\circ\text{C}$, unless otherwise noted.



TYPICAL PERFORMANCE CHARACTERISTICS *(continued)*

$T_A = +25^\circ\text{C}$, unless otherwise noted.




TYPICAL PERFORMANCE CHARACTERISTICS *(continued)*

$T_A = +25^\circ\text{C}$, unless otherwise noted.


Small Signal Pulse Response

$A_V = 1$, $V_+ = 2.5\text{V}$, $V_- = -2.5\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$




Small Signal Pulse Response

$A_V = 1$, $V_+ = 1.25\text{V}$, $V_- = -1.25\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$




Small Signal Pulse Response

$A_V = 1$, $V_+ = 2.5\text{V}$, $V_- = -2.5\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 50\text{pF}$




Small Signal Pulse Response

$A_V = 1$, $V_+ = 1.25\text{V}$, $V_- = -1.25\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 50\text{pF}$




Small Signal Pulse Response

$A_V = -1$, $V_+ = 2.5\text{V}$, $V_- = -2.5\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$




Small Signal Pulse Response

$A_V = -1$, $V_+ = 1.25\text{V}$, $V_- = -1.25\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$




Small Signal Pulse Response

$A_V = -1$, $V_+ = 2.5\text{V}$, $V_- = -2.5\text{V}$
 $R_L = 5\text{k}\Omega$, $C_L = 8\text{pF}$



Small Signal Pulse Response

$A_V = -1$, $V_+ = 1.25\text{V}$, $V_- = -1.25\text{V}$
 $R_L = 5\text{k}\Omega$, $C_L = 8\text{pF}$




TYPICAL PERFORMANCE CHARACTERISTICS *(continued)*

$T_A = +25^\circ\text{C}$, unless otherwise noted.


Large Signal Pulse Response

$A_V = 1$, $V_+ = 2.5\text{V}$, $V_- = -2.5\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$




Large Signal Pulse Response

$A_V = 1$, $V_+ = 1.25\text{V}$, $V_- = -1.25\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$




Rail to Rail Output Operation

$A_V = -2$, $V_+ = 2.5\text{V}$, $V_- = -2.5\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$




Rail to Rail Output Operation

$A_V = -2$, $V_+ = 1.25\text{V}$, $V_- = -1.25\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$




Rail to Rail Output Operation

$A_V = 2$, $V_+ = 2.5\text{V}$, $V_- = -2.5\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$



Rail to Rail Output Operation

$A_V = 2$, $V_+ = 1.25\text{V}$, $V_- = -1.25\text{V}$
 $R_L = 1\text{M}\Omega$, $C_L = 8\text{pF}$



APPLICATION INFORMATION


Power Supply Bypassing

Regular supply bypassing techniques are recommended. A 10 μ F capacitor in parallel with a 0.1 μ F capacitor on both the positive and negative supplies is ideal. For the best


performance, all bypassing capacitors should be located as close to the op amp as possible and all capacitors should be low ESL (Equivalent Series Inductance) and low ESR (Equivalent Series Resistance). Surface mount ceramic capacitors are ideal.

PACKAGE INFORMATION


TSOT23-5




TOP VIEW




RECOMMENDED LAND PATTERN



FRONT VIEW



SIDE VIEW



DETAIL A

NOTE:

- 1) ALL DIMENSIONS ARE IN MILLIMETERS.
- 2) PACKAGE LENGTH DOES NOT INCLUDE MOLD FLASH, PROTRUSION OR GATE BURR.
- 3) PACKAGE WIDTH DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSION.
- 4) LEAD COPLANARITY (BOTTOM OF LEADS AFTER FORMING) SHALL BE 0.10 MILLIMETERS MAX.
- 5) DRAWING CONFORMS TO JEDEC MO-193, VARIATION AA.
- 6) DRAWING IS NOT TO SCALE.

NOTICE: The information in this document is subject to change without notice. Users should warrant and guarantee that third party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.