13/11/2012 www.crouzet.com



Sandwich communication extensions XN05 Part number 88970270



- Exchange of input/output state or of internal values via communication networks
- Power supply via the controller

Part numbers

	Туре	Description	Supply
88970270	XN05	Ethernet protocol TCP Modbus extension	Via the 24 V DC controller

Specifications

General environment characteristics for CB, CD, XD, XB, XR and XE product types Certifications UL, CSA

Certifications	UL, CSA GL: except for 88 970 32x (pending)
Conformity to standards (with the low voltage directive	In accordance with 73/23/EEC :
and EMC directive)	EN (IEC) 61131-2 (Open equipment)
Conformity with the EMC directive	In accordance with 89/336/EEC :
	EN (IEC) 61131-2 (Zone B)
	EN (IEC) 61000-6-2,
	EN (IEC) 61000-6-3 (*) EN (IEC) 61000-6-4
	(*) Except configuration (88 970 1.1 or 88 970 1.2) + (88 970 250 or 88 970 270) + 88 970 241 class A (class B : using in metallic
	cabinet)
Earthing	None
Protection rating	In accordance with IEC/EN 60529:
	IP40 on front panel
	IP20 on terminal block
Overvoltage category	3 in accordance with IEC/EN 60664-1
Pollution	Degree : 2 in accordance with IEC/EN 61131-2
Max operating Altitude	Operation: 2000 m Transport: 3,048 m
Mechanical resistance	Immunity to vibrations IEC/EN 60068-2-6, Fc test
	Immunity to shock IEC/EN 60068-2-27, Fa test
Resistance to electrostatic discharge	Immunity to ESD IEC/EN 61000-4-2, level 3
Resistance to HF interference	Immunity to radiated electrostatic fields
	IEC/EN 61000-4-3,
	Immunity to fast transients (burst immunity) IEC/EN 61000-4-4, level 3
	Immunity to shock waves
	IEC/EN 61000-4-5
	Radio frequency in common mode
	IEC/EN 61000-4-6, level 3
	Voltage dips and breaks (AC) IEC/EN 61000-4-11
	Immunity to damped oscillatory waves
	IEC/EN 61000-4-12
Conducted and radiated emissions	Class B (*) in accordance with EN 55022/11 group 1
	(*) Except configuration (88 970 1.1 or 88 970 1.2) + (88 970 250 or 88 970 270) + 88 970 241 class A (class B in metallic cabinet)
Operating temperature	-20+55 °C (+40 °C in a non-ventilated enclosure) in accordance with IEC/EN 60068-2-1 and IEC/EN 60068-2-2
Storage temperature	-40 →+70 °C in accordance with IEC/EN 60068-2-1 and IEC/EN 60068-2-2
Relative humidity	95 % max. (no condensation or dripping water) in accordance with IEC/EN 60068-2-30
Mounting	On symmetrical DIN profile, 35 x 7.5 mm and 35 mm x 15 or panel (2 x 4 mm Ø) Flexible wire with ferrule =
Screw terminals connection capacity	
	1 conductor : 0.25 to 2.5 mm ² (AWG 24AWG 14)
	2 conductors 0.25 to 0.75 mm ² (AWG 24AWG 18) Semi-rigid wire =
	1 conductor : 0.2 to 2.5 mm ² (AWG 25AWG 14) Rigid wire =
	1 conductor : 0.2 to 2.5 mm ² (AWG 25AWG 14)
	2 conductors 0.2 to 1.5 mm ² (AWG 25AWG 16)
	Tightening torque = 0.5 N.m (4.5 lb-in) (tighten using screwdriver diam. 3.5 mm)
	(· · ·) (· · · ·) (· · · · · · · ·

Characteristics of communication extensions

General characteristics

See page 22, except : See page 22, except :

13/11/2012 www.crouzet.com

3/11/2012				www.crouzei.co
Certifications	UL, CSA, GL (UL, CSA : 88972250)		UL, CSA	
Farthing	, i i i i i i i i i i i i i i i i i i i		GL pending Yes, refer to the quick reference guide supplied with the	
Earthing Yes, refer to the quick reference guide supplied			product	
Operating temperature	-20 →+55 °C (+40 °C in a non-ventilated enclosure) in accordance with IEC/EN 60068-2-1 and IEC/EN 60068-2-2		0 →+55 °C (+40 °C in a non-ventilated enclosure) in accordance with IEC 60068-2-1 and IEC 60068-2-2	
Cable length	Maximum length of the network : 1000 m	n (9600 Baud maxi, AWG26	Maximum length between 2	controllers : 100 m
Communication parameters	00070070			
38970250 & 88972250 Type of link	88970270 2 or 4-wire ; RTU or ASCII			_
Fransmission rate (Bauds)	1200, 2400, 4800, 9600, 19200, 28800,	38400, 57600		
Parity	None ; even ; odd			-
Addressing	1 →247			Static or dynamic
Characteristics of exchanges				
88970250	88972250		88970270	
_adder programming				
mage of smart relay I/O	4	4	-	
Status	1	1	-	
Function blocks programming	4			0
Read-words Read/Write	4 8 4 8			8 8
Clock words	4 1			4
Status" words	1 1	_		1
Processing characteristics of CB, CD, XD & XB product				
ypes	CD VD Diorless with A Process (40)	o atoro		
.CD display	CD, XD: Display with 4 lines of 18 chara-			
Programming method Program size	Ladder or function blocks/SFC (Grafcet) Ladder: 120 lines			
Togram 3/20	Function blocks : CB, CD : typically 350 blocks XB, XD : typically 700 blocks			
Program memory	Flash EEPROM			
Removable memory	EEPROM			
Data memory	368 bits/200 words			
Back-up time in the event of power failure	Program and settings in the controller : 10 years Program and settings in the plug-in memory : 10 years Data memory : 10 years			
Cycle time	Ladder : typically 20 ms Function blocks : 6 →90 ms			
Response time	Input acquisition time + 1 to 2 cycle times			
Clock data retention	10 years (lithium battery) at 25 °C			
Clock drift	Drift < 12 min/year (at 25 °C) 6 s/month (at 25 °C with user-definable correction of drift)			
Timer block accuracy	1 % ± 2 cycle times	,		
Start up time on power up	< 1,2 s			
Characteristics of products with AC power suppli	ed			
Supply				
Nominal voltage	24 V AC		0 →240 V AC	
Operating limits	-15 % / +20 % or 20.4 VAC→28.8 VAC		5 % / +10 % 85 VAC→264 VAC	
Supply frequency range	50/60 Hz (+4 % / -6 %)	50	/60 Hz (+4 % / -6 %) or 47 →53	
and the first of the second second	or 47→53 Hz/57 < 63 Hz			Hz/57 < 63 Hz
			,	Hz/57 < 63 Hz
	10 ms (repetition 20 times)		ms (repetition 20 times)	Hz/57 < 63 Hz
	10 ms (repetition 20 times) CB12-CD12-XD10-XB10 : 4 VA CB20-CD20 : 6 VA XD10 with extension - XD26-XB26 : 7.5	CE CE VA XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26-	XB26 : 12 VA
Max. absorbed power	10 ms (repetition 20 times) CB12-CD12-XD10-XB10 : 4 VA CB20-CD20 : 6 VA XD10 with extension - XD26-XB26 : 7.5 XD26-XB26 with extension : 10 VA	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension : 17 V	XB26 : 12 VA
vlax. absorbed power	10 ms (repetition 20 times) CB12-CD12-XD10-XB10 : 4 VA CB20-CD20 : 6 VA XD10 with extension - XD26-XB26 : 7.5	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26-	XB26 : 12 VA
Max. absorbed power solation voltage nputs	10 ms (repetition 20 times) CB12-CD12-XD10-XB10 : 4 VA CB20-CD20 : 6 VA XD10 with extension - XD26-XB26 : 7.5 XD26-XB26 with extension : 10 VA 1780 V AC	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension : 17 Va 180 V AC	XB26 : 12 VA A
Max. absorbed power Isolation voltage Inputs Input voltage	10 ms (repetition 20 times) CB12-CD12-XD10-XB10 : 4 VA CB20-CD20 : 6 VA XD10 with extension - XD26-XB26 : 7.5 XD26-XB26 with extension : 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension : 17 V	XB26 : 12 VA A
vlax. absorbed power solation voltage nputs nput voltage	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension : 17 V 180 V AC 100 →240 V AC (-15 % / +10	XB26 : 12 VA A
vlax. absorbed power solation voltage nputs nput voltage nput current	10 ms (repetition 20 times) CB12-CD12-XD10-XB10 : 4 VA CB20-CD20 : 6 VA XD10 with extension - XD26-XB26 : 7.5 XD26-XB26 with extension : 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension : 17 V. 180 V AC 100 →240 V AC (-15 % / +10 0,24 mA @ 85 V AC	XB26 : 12 VA A
solation voltage nputs nput voltage nput current	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC	CE CE VA XI XI	ms (repetition 20 times) 312-CD12-XD10-XB10 : 7 VA 320-CD20 : 11 VA 310-XB10 with extension-XD26- 326-XB26 with extension : 17 V 380 V AC 100 →240 V AC (-15 % / +10 0,24 mA @ 85 V AC 0,75 mA @ 264 V AC	XB26 : 12 VA A
Max. absorbed power solation voltage nputs nput voltage nput current nput impedance Logic 1 voltage threshold Making current at logic state 1	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC 4.6 kΩ ≥ 14 V AC >2 mA	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension : 17 V. 180 V AC 100 →240 V AC (-15 % / +10 0,24 mA @ 85 V AC 0,75 mA @ 264 V AC 350 kΩ	XB26 : 12 VA A
Max. absorbed power solation voltage nputs nput voltage nput current nput impedance logic 1 voltage threshold Making current at logic state 1 logic 0 voltage threshold	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC 4.6 kΩ ≥ 14 V AC >2 mA ≤ 5 V AC	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension : 17 V. 180 V AC 100 →240 V AC (-15 % / +10 0,24 mA @ 85 V AC 0,75 mA @ 264 V AC 350 kΩ ≥ 79 V AC >0.17 mA ≤ 20 V AC (≤ 28 V AC : XE10,	XB26 : 12 VA A %)
Max. absorbed power solation voltage nputs nput voltage nput current nput impedance Logic 1 voltage threshold Making current at logic state 1 Logic 0 voltage threshold Release current at logic state 0	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC 4.6 kΩ ≥ 14 V AC >2 mA ≤ 5 V AC <0.5 mA	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10: 7 VA 120-CD20: 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension: 17 V. 180 V AC 100 →240 V AC (-15 % / +10 0,24 mA @ 85 V AC 0,75 mA @ 264 V AC 350 kΩ ≥ 79 V AC >0.17 mA ≤ 20 V AC (≤ 28 V AC : XE10, <0.5 mA	XB26 : 12 VA A %)
Solation voltage nputs nput voltage nput current nput impedance Logic 1 voltage threshold Making current at logic state 1 Logic 0 voltage threshold Release current at logic state 0	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC 4.6 kΩ ≥ 14 V AC >2 mA ≤ 5 V AC	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10 : 7 VA 120-CD20 : 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension : 17 V. 180 V AC 100 →240 V AC (-15 % / +10 0,24 mA @ 85 V AC 0,75 mA @ 264 V AC 350 kΩ ≥ 79 V AC >0.17 mA ≤ 20 V AC (≤ 28 V AC : XE10,	XB26 : 12 VA A %)
Max. absorbed power Isolation voltage Inputs Input voltage Input current Input impedance Logic 1 voltage threshold Making current at logic state 1 Logic 0 voltage threshold Release current at logic state 0 Response time with LADDER programming	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC 4.6 kΩ ≥ 14 V AC >2 mA ≤ 5 V AC <0.5 mA 50 ms State 0 →1 (50/60 Hz) Configurable in increments of 10 ms 50 ms min. up to 255 ms	CE CE VA XI XI	ms (repetition 20 times) 112-CD12-XD10-XB10: 7 VA 120-CD20: 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension: 17 V. 180 V AC 100 \rightarrow 240 V AC (-15 % / +10 0,24 mA @ 85 V AC 0,75 mA @ 264 V AC 350 kΩ ≥ 79 V AC >0.17 mA ≤ 20 V AC (≤ 28 V AC : XE10, <0.5 mA 50 ms State 0 < 1 (50/60 Hz) Configurable in increments of 50 ms min. up to 255 ms	XB26 : 12 VA A %)
Max. absorbed power Isolation voltage Inputs Input voltage Input current Input impedance Logic 1 voltage threshold Making current at logic state 1 Logic 0 voltage threshold Release current at logic state 0 Response time with LADDER programming Response time with function blocks programming	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC 4.6 kΩ ≥ 14 V AC >2 mA ≤ 5 V AC <0.5 mA 50 ms State 0 →1 (50/60 Hz) Configurable in increments of 10 ms	CE CE VA XI XI 17	ms (repetition 20 times) 112-CD12-XD10-XB10: 7 VA 120-CD20: 11 VA 110-XB10 with extension-XD26- 126-XB26 with extension: 17 V. 180 V AC 100 \rightarrow 240 V AC (-15 % / +10 0,24 mA @ 85 V AC 0,75 mA @ 264 V AC 350 kΩ ≥ 79 V AC >0.17 mA ≤ 20 V AC (≤ 28 V AC : XE10, <0.5 mA 50 ms State 0 < 1 (50/60 Hz) Configurable in increments of 50 ms min. up to 255 ms State 0 \rightarrow 1 (50/60 Hz)	XB26 : 12 VA A %) XR06, XR10, XR14)
Solation voltage Inputs Input voltage Input voltage Input current Input impedance Logic 1 voltage threshold Input impedance Input current at logic state 1 Input coltage threshold Input impedance Input imped	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC 4.6 kΩ ≥ 14 V AC >2 mA ≤ 5 V AC <0.5 mA 50 ms State 0 →1 (50/60 Hz) Configurable in increments of 10 ms 50 ms min. up to 255 ms State 0 →1 (50/60 Hz) In accordance with cycle time (Tc) and i	CE CE VA XI XI 17	ms (repetition 20 times) ms (repetition 20 ti	XB26 : 12 VA A %) XR06, XR10, XR14)
Max. absorbed power Isolation voltage Inputs Input voltage Input current Input impedance Logic 1 voltage threshold Making current at logic state 1 Logic 0 voltage threshold Release current at logic state 0 Response time with LADDER programming Response time with function blocks programming Maximum counting frequency Sensor type	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC 4.6 kΩ ≥ 14 V AC >2 mA ≤ 5 V AC <0.5 mA 50 ms State 0 →1 (50/60 Hz) Configurable in increments of 10 ms 50 ms min. up to 255 ms State 0 →1 (50/60 Hz) In accordance with cycle time (Tc) and i 1/ ((2 x Tc) + Tr)	CE CE VA XI XI 17	ms (repetition 20 times) 112 -CD12-XD10-XB10: 7 VA 120 -CD20: 11 VA 110 -XB10 with extension-XD26- 126 -XB26 with extension: 17 V. 1100 -240 V AC (-15 % / +10 1100 -240 V AC (-15 % / +10 1100 -240 V AC 1100 -350 V AC 1100 -360 V	XB26 : 12 VA A %) XR06, XR10, XR14)
Immunity from micro power cuts Max. absorbed power Isolation voltage Inputs Input voltage Input current Input impedance Logic 1 voltage threshold Making current at logic state 1 Logic 0 voltage threshold Release current at logic state 0 Response time with LADDER programming Response time with function blocks programming Maximum counting frequency Sensor type Input type Isolation between power supply and inputs Isolation between inputs	10 ms (repetition 20 times) CB12-CD12-XD10-XB10: 4 VA CB20-CD20: 6 VA XD10 with extension - XD26-XB26: 7.5 XD26-XB26 with extension: 10 VA 1780 V AC 24 V AC (-15 % / +20 %) 4,4 mA @ 20,4 V AC 5,2 mA @ 24,0 V AC 6,3 mA @ 28,8 V AC 4.6 kΩ ≥ 14 V AC >2 mA ≤ 5 V AC <0.5 mA 50 ms State 0 →1 (50/60 Hz) Configurable in increments of 10 ms 50 ms min. up to 255 ms State 0 →1 (50/60 Hz) In accordance with cycle time (Tc) and i 1/ ((2 x Tc) + Tr) Contact or 3-wire PNP	CE CE VA XI XI 17	ms (repetition 20 times) 112 -CD12-XD10-XB10: 7 VA 120 -CD20: 11 VA 110 -XB10 with extension-XD26- 126 -XB26 with extension: 17 V. $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +10 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +10 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +10 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +10 $1100 \rightarrow 240 \text{ V AC}$ (-264 V AC $1100 \rightarrow 240 \text{ V AC}$ (-275 % / +10 $1100 \rightarrow 240 \text{ V AC}$ (-284 V AC $1100 \rightarrow 240 \text{ V AC}$ (-284 V AC $1100 \rightarrow 240 \text{ V AC}$ (-284 V AC $1100 \rightarrow 240 \text{ V AC}$ (-285 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-287 V AC : XE10, <0.5 mA $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +100 $1100 \rightarrow 240 \text{ V AC}$ (-15 % / +10	XB26 : 12 VA A %)

13/11/2012 WWW.crouzet.com
Status indicator On LCD screen for CD and XD On LCD screen for CD and XD

Status indicator	On LCD screen for CD and XD		On LCD screen for CD and XD
Characteristics of relay outputs common to the en	ntire range		
Max. breaking voltage	5 →30 V DC		
	24 →250 V AC		
Breaking current	CB-CD-XB10-XD10-XR06-XR10 : 8 A		
	XD26-XB26 : 8 x 8 A relays, 2 x 5 A relays		
	XE10 : 4 x 5 A relays		
	XR14: 4 x 8 A relays, 2 x 5 A relays		
Electrical durability for 500 000 operating cycles	Usage category DC-12 : 24 V, 1.5 A Usage category DC-13 : 24 V (L/R = 10 ms), 0.6 A		
	Usage category AC-12 : 230 V, 1.5 A	0.6 A	
	Usage category AC-12 : 230 V, 1.3 A		
Max. Output Common Current	12A for O8,O9,OA		
Minimum switching capacity	10 mA (at minimum voltage of 12 V)		
Minimum load	12 V, 10 mA		
Maximum rate	Off load : 10 Hz		
	At operating current : 0.1 Hz		
Mechanical life	10,000,000 operations (cycles)		
Voltage for withstanding shocks	In accordance with IEC/EN 60947-1 and IEC/EN 60664-1 : 4 kV		
Response time	Make 10 ms		
	Release 5 ms		
Built-in protections	Against short-circuits : None		
	Against overvoltages and overloads : None		
Status indicator	On LCD screen for CD and XD		
Characteristics of product with DC power supplied	d		
Supply			
Nominal voltage	12 V DC	24 V DC	
Operating limits	-13 % / +20 %	-20 % / +25 %	
	or 10.4 V DC < 14.4 V DC (including ripple)	or 19.2 V DC < 30 V	
Immunity from micro power cuts	≤ 1 ms (repetition 20 times)	≤ 1 ms (repetition 20	•
Max. absorbed power	CB12 with solid state outputs : 1.5 W		ith solid state outputs - XD10-XB10 with solid state outputs : 3 W
	CD12 : 1.5 W CD20 : 2.5 W	XD10-XB10 with rela	· · ·
	XD26-XB26 : 3 W	XD26-XB26 with soli	ay outputs-XD26 with relay outputs : 6 W
	XD26-XB26 with extension : 5 W	XD10-XB10 with exte	
	XD26 with solid state outputs : 2.5 W	XD26-XB26 with exte	
Protection against polarity inversions	Yes	Yes	
Digital inputs (I1 to IA and IH to IY)			
Input voltage	12 V DC (-13 % / +20 %)		24 V DC (-20 % / +25 %)
Input current	3,9 mA @ 10,44 V DC		2,6 mA @ 19,2 V DC
	4,4 mA @ 12,0 V DC		3,2 mA @ 24 V DC
	5,3 mA @ 14,4 VDC		4,0 mA @ 30,0 VDC
Input impedance	2.7 kΩ		7.4 kΩ
Logic 1 voltage threshold	≥7 V DC		≥ 15 V DC
Making current at logic state 1	≥2 mA		≥2.2 mA
Logic 0 voltage threshold	≤ 3 V DC <0.9 mA		≤ 5 V DC <0.75 mA
Release current at logic state 0 Response time			
Maximum counting frequency	 1 →2 cycle times + 6 ms I1 & I2 : Ladder (1 k Hz) & FBD (Up to 6 k Hz) 		1 →2 cycle times + 6 ms 11 & I2 : Ladder (1 k Hz) & FBD (Up to 6 k Hz)
Waximum counting requertey	I3 to IA & IH to IY: in accordance with cycle time (Tc) and input		13 to IA & IH to IY: in accordance with cycle time (Tc) and input
	response time (Tr) : 1/ ((2 x Tc) + Tr)		response time (Tr) : 1/ ((2 x Tc) + Tr)
Sensor type	Contact or 3-wire PNP		Contact or 3-wire PNP
Conforming to IEC/EN 61131-2	Type 1		Type 1
Input type	Resistive		Resistive
Isolation between power supply and inputs	None		None
Isolation between inputs	None		None
Protection against polarity inversions	Yes		Yes
Status indicator	On LCD screen for CD and XD		On LCD screen for CD and XD
Analogue or digital inputs (IB to IG)			
CB12-CD12-XD10-XB10	4 inputs IB →IE		4 inputs IB →IE
CB20-CD20-XB26-XD26	6 inputs IB →IG		6 inputs IB →IG
Inputs used as analogue inputs			
Measurement range	$(0 \rightarrow 10 \text{ V}) \text{ or } (0 \rightarrow \text{V power supply})$		$(0 \rightarrow 10 \text{ V}) \text{ or } (0 \rightarrow \text{V power supply})$
Input impedance	14 kΩ		12 kΩ
Input voltage	14.4 V DC max		30 V DC max
Value of LSB	14 mV		29 mV
Input type	Common mode		Common mode
Resolution	10 bit at maximum input voltage		10 bit at maximum input voltage
Conversion time	Controller cycle time		Controller cycle time
Accuracy at 25 °C	± 5 %		± 5 %
Accuracy at 55 °C	± 6.2 %		± 6.2 %
Repeat accuracy at 55 °C	±2%		± 2 %
Isolation between analogue channel and power supply None			None
Cable length	10 m maximum, with shielded cable (sensor	not isolated)	10 m maximum, with shielded cable (sensor not isolated)
Protection against polarity inversions	Yes		Yes
Potentiometer control	2.2 kΩ/0.5 W (recommended) 10 kΩ max.		2.2 $k\Omega/0.5$ W (recommended) 10 $k\Omega$ max.
Inpute used as digital inpute	TO NAZ IIIGA.		10 N22 IIIQA.
Inputs used as digital inputs Input voltage	12 V DC (-13 % / +20 %)		24 V DC (-20 % / +25 %)
Input current	0,7 mA @ 10,44 VDC		1,6 mA @ 19,2 VDC
- A Par out of R	0,9 mA @ 12,0 VDC		2,0 mA @ 24,0 V DC

13/11/2012 www.crouzet.com

13/11/2012		www.crouzet.con
	1,0 mA @ 14,4VDC	2,5 mA @ 30,0 VDC
Input impedance	14 kΩ	12 kΩ
Logic 1 voltage threshold	≥7 V DC	≥ 15 VDC
Making current at logic state 1	≥0.5 mA	≥1.2 mA
Logic 0 voltage threshold	≤ 3 V DC	≤5 V DC
Release current at logic state 0	≤0.2 mA	≤0.5 mA
Response time	1 →2 cycle times	1 →2 cycle times
Maximum counting frequency	In accordance with cycle time (Tc) and input response time (Tr) : 1/ ((2 x Tc) + Tr)	In accordance with cycle time (Tc) and input response time (Tr) : 1/ ($(2 \times Tc) + Tr)$
Sensor type	Contact or 3-wire PNP	Contact or 3-wire PNP
Conforming to IEC/EN 61131-2	Type 1	Type 1
Input type	Resistive	Resistive
Isolation between power supply and inputs	None	None
Isolation between inputs	None	None
Protection against polarity inversions	Yes	Yes
Status indicator	On LCD screen for CD and XD	On LCD screen for CD and XD
Characteristics of relay outputs common to the entire range		
Max. breaking voltage	5 →30 V DC 24 →250 V AC	
Max. Output Common Current	12A (10A UL) for O8,O9,OA	
Breaking current	CB-CD-XD10-XB10-XR06-XR10 : 8 A	
	XD26-XB26 : 8 x 8 A relays, 2 x 5 A relays XE10 : 4 x 5 A relays XR14 : 4 x 8 A relays, 2 x 5 A relays	
Electrical durability for 500 000 operating cycles	Usage category DC-12: 24 V, 1.5 A Usage category DC-13: 24 V (L/R = 10 ms), 0.6 A Usage category AC-12: 230 V, 1.5 A Usage category AC-15: 230 V, 0.9 A	
Minimum switching capacity	10 mA (at minimum voltage of 12 V)	
Minimum load	12 V, 10 mA	
Maximum rate	Off load : 10 Hz	
	At operating current : 0.1 Hz	
Mechanical life	10,000,000 operations (cycles)	
Voltage for withstanding shocks	In accordance with IEC/EN 60947-1 and IEC/EN 60664-1 : 4 kV	
Response time	Make 10 ms Release 5 ms	
Built-in protections	Against short-circuits : None Against overvoltages and overloads : None	
Status indicator	On LCD screen for CD and XD	
Digital / PWM solid state output		
PWM solid state output*	CB12 : O4 XD26 : O4 →O7	CD12-XD10-XB10 : O4 CD20-XD26-XB26 : O4 →O7
* Only available with "FBD" programming language	* Only available with "FBD" programming language	
Breaking voltage	10.4 →30 VDC	19.2 →30 VDC
Nominal voltage	12-24 V DC	24 V DC
Nominal current	0.5 A	0.5 A
Max. breaking current	0,625 A	0,625 A
Voltage drop	≤ 2 V for I = 0.5 A (at state 1)	≤ 2 V for I = 0.5 A (at state 1)
Response time	Make ≤ 1 ms Release ≤ 1 ms	Make ≤ 1 ms Release ≤ 1 ms
Built-in protections	Against overloads and short-circuits: Yes Against overvoltages (*): Yes Against inversions of power supply: Yes (*) In the absence of a volt-free contact between the output of the logic controller and the load	Against overloads and short-circuits: Yes Against overvoltages (*): Yes Against inversions of power supply: Yes (*) In the absence of a volt-free contact between the output of the logic controller and the load
Min. load	1 mA	1 mA
Maximum incandescent load	0,2 A / 12 V DC 0,1 A / 24 V DC	0,1 A / 24 V DC
Galvanic isolation	No	No
PWM frequency	14.11 Hz 56.45 Hz 112.90 Hz 225.80 Hz 451.59 Hz 1806.37 Hz	14.11 Hz 56.45 Hz 112.90 Hz 225.80 Hz 451.59 Hz 1806.37 Hz
PWM cyclic ratio	0 →100 % (256 steps for CD, XD and 1024 for XA)	0 →100 % (256 steps for CD, XD and 1024 for XA)
PWM accuracy at 120 Hz	< 5 % (20 % →80 %) load at 10 mA	< 5 % (20 % →80 %) load at 10 mA
PWM accuracy at 500 Hz	< 10 % (20 % →80 %) load at 10 mA	< 10 % (20 % →80 %) load at 10 mA
		On LCD screen for CD and XD

Dimensions (mm) XN03 - XN05 - XN06

13/11/2012 www.crouzet.com

