



## AM26LS32Ax, AM26LS33Ax Quadruple Differential Line Receivers

### 1 Features

- AM26LS32A Devices Meet or Exceed the Requirements of ANSI TIA/EIA-422-B, TIA/EIA-423-B, and ITU Recommendations V.10 and V.11
- AM26LS32A Devices Have  $\pm 7$ -V Common-Mode Range With  $\pm 200$ -mV Sensitivity
- AM26LS33A Devices Have  $\pm 15$ -V Common-Mode Range With  $\pm 500$ -mV Sensitivity
- Input Hysteresis 50 mV Typical
- Operate From a Single 5-V Supply
- Low-Power Schottky Circuitry
- 3-State Outputs
- Complementary Output-Enable Inputs
- Input Impedance 12 k $\Omega$  Minimum
- Open Input Fail-Safe

### 2 Applications

- High-Reliability Automotive Applications
- Factory Automation
- ATM and Cash Counters
- Smart Grids
- AC and Servo Motor Drives

### 3 Description

The AM26LS32Ax and AM26LS33Ax devices are quadruple differential line receivers for balanced and unbalanced digital data transmission. The enable function is common to all four receivers and offers a choice of active-high or active-low input. The 3-state outputs permit connection directly to a bus-organized system. Fail-safe design ensures that, if the inputs are open, the outputs always are high.

Compared to the AM26LS32 and the AM26LS33, the AM26LS32A and AM26LS33A incorporate an additional stage of amplification to improve sensitivity. The input impedance has been increased, resulting in less loading of the bus line. The additional stage has increased propagation delay; however, this does not affect interchangeability in most applications.


The AM26LS32AC and AM26LS33AC are characterized for operation from 0°C to 70°C. The AM26LS32AI is characterized for operation from –40°C to 85°C. The AM26LS32AM and AM26LS33AM are characterized for operation over the full military temperature range of –55°C to 125°C.

#### Device Information<sup>(1)</sup>

| PART NUMBER              | PACKAGE    | BODY SIZE (NOM)           |
|--------------------------|------------|---------------------------|
| AM26LS3xAC<br>AM26LS32AI | PDIP (16)  | 19.30 mm $\times$ 6.35 mm |
|                          | SOIC (16)  | 9.90 mm $\times$ 3.90 mm  |
| AM26LS32AC               | SO (16)    | 10.20 mm $\times$ 5.30 mm |
|                          | TSSOP (16) | 5.00 mm $\times$ 4.40 mm  |
| AM26LS3xAM               | CDIP (16)  | 21.34 mm $\times$ 6.92 mm |
|                          | LCCC (20)  | 8.90 mm $\times$ 8.90 mm  |

(1) For all available packages, see the orderable addendum at the end of the data sheet.

#### Logic Diagram (Positive Logic)



Copyright © 2016, Texas Instruments Incorporated

Pin numbers are for D, N, NS, or PW packages only.



## Table of Contents

|                                                  |           |                                                                  |           |
|--------------------------------------------------|-----------|------------------------------------------------------------------|-----------|
| <b>1 Features</b> .....                          | <b>1</b>  | 8.3 Feature Description .....                                    | <b>11</b> |
| <b>2 Applications</b> .....                      | <b>1</b>  | 8.4 Device Functional Modes .....                                | <b>11</b> |
| <b>3 Description</b> .....                       | <b>1</b>  | <b>9 Application and Implementation</b> .....                    | <b>12</b> |
| <b>4 Revision History</b> .....                  | <b>2</b>  | 9.1 Application Information .....                                | <b>12</b> |
| <b>5 Pin Configuration and Functions</b> .....   | <b>3</b>  | 9.2 Typical Application .....                                    | <b>12</b> |
| <b>6 Specifications</b> .....                    | <b>4</b>  | <b>10 Power Supply Recommendations</b> .....                     | <b>13</b> |
| 6.1 Absolute Maximum Ratings .....               | 4         | <b>11 Layout</b> .....                                           | <b>13</b> |
| 6.2 ESD Ratings .....                            | 4         | 11.1 Layout Guidelines .....                                     | <b>13</b> |
| 6.3 Recommended Operating Conditions .....       | 4         | 11.2 Layout Example .....                                        | <b>14</b> |
| 6.4 Thermal Information .....                    | 5         | <b>12 Device and Documentation Support</b> .....                 | <b>15</b> |
| 6.5 Electrical Characteristics .....             | 5         | 12.1 Related Links .....                                         | <b>15</b> |
| 6.6 Switching Characteristics .....              | 6         | 12.2 Receiving Notification of Documentation Updates .....       | <b>15</b> |
| 6.7 Dissipation Ratings .....                    | 6         | 12.3 Community Resources .....                                   | <b>15</b> |
| 6.8 Typical Characteristics .....                | 7         | 12.4 Trademarks .....                                            | <b>15</b> |
| <b>7 Parameter Measurement Information</b> ..... | <b>9</b>  | 12.5 Electrostatic Discharge Caution .....                       | <b>15</b> |
| <b>8 Detailed Description</b> .....              | <b>11</b> | 12.6 Glossary .....                                              | <b>15</b> |
| 8.1 Overview .....                               | 11        | <b>13 Mechanical, Packaging, and Orderable Information</b> ..... | <b>15</b> |
| 8.2 Functional Block Diagram .....               | 11        |                                                                  |           |


## 4 Revision History

NOTE: Page numbers for previous revisions may differ from page numbers in the current version.


| Changes from Revision E (October 2007) to Revision F                                                                                                                                                                                                                                                                                                                              | Page     |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------|
| • Added <i>Applications</i> section, <i>ESD Ratings</i> table, <i>Feature Description</i> section, <i>Device Functional Modes</i> , <i>Application and Implementation</i> section, <i>Power Supply Recommendations</i> section, <i>Layout</i> section, <i>Device and Documentation Support</i> section, and <i>Mechanical, Packaging, and Orderable Information</i> section ..... | <b>1</b> |
| • Changed $R_{\theta JA}$ values in the <i>Thermal Information</i> table: 73 to 75.7 for (D), 67 to 45.3 (N), 64 to 75.8 (NS), and 108 to 102.7 (PW) .....                                                                                                                                                                                                                        | <b>5</b> |

## 5 Pin Configuration and Functions

**D, J, N, NS, and PW Package  
16-Pin SOIC, CDIP, PDIP, SO, and TSSOP  
Top View**



**FK Package  
20-Pin LCCC  
Top View**



NC - No internal connection

### Pin Functions

| NAME            | PIN                            |              | I/O | DESCRIPTION                                   |
|-----------------|--------------------------------|--------------|-----|-----------------------------------------------|
|                 | SOIC, CDIP, PDIP,<br>SO, TSSOP | LCCC         |     |                                               |
| 1A              | 2                              | 3            | I   | RS422/RS485 differential input (noninverting) |
| 1B              | 1                              | 2            | I   | RS422/RS485 differential input (inverting)    |
| 1Y              | 3                              | 4            | O   | Logic level output                            |
| 2A              | 6                              | 8            | I   | RS422/RS485 differential input (noninverting) |
| 2B              | 7                              | 9            | I   | RS422/RS485 differential input (inverting)    |
| 2Y              | 5                              | 7            | O   | Logic level output                            |
| 3A              | 10                             | 13           | I   | RS422/RS485 differential input (noninverting) |
| 3B              | 9                              | 12           | I   | RS422/RS485 differential input (inverting)    |
| 3Y              | 11                             | 14           | O   | Logic level output                            |
| 4A              | 14                             | 18           | I   | RS422/RS485 differential input (noninverting) |
| 4B              | 15                             | 19           | I   | RS422/RS485 differential input (inverting)    |
| 4Y              | 13                             | 17           | O   | Logic level output                            |
| $\overline{G}$  | 12                             | 15           | I   | Active-Low select                             |
| G               | 4                              | 5            | I   | Active-High select                            |
| GND             | 8                              | 10           | —   | Ground                                        |
| NC              | —                              | 1, 6, 11, 16 | —   | No internal connection                        |
| V <sub>CC</sub> | 16                             | 20           | —   | Power supply                                  |

## 6 Specifications

### 6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)<sup>(1)</sup>

|                                                     |                        | MIN                                     | MAX | UNIT |
|-----------------------------------------------------|------------------------|-----------------------------------------|-----|------|
| Supply voltage, $V_{CC}$ <sup>(2)</sup>             |                        |                                         | 7   | V    |
| Input voltage, $V_I$                                | Any differential input |                                         | ±25 | V    |
|                                                     | Other inputs           |                                         | 7   |      |
| Differential input voltage, $V_{ID}$ <sup>(3)</sup> |                        |                                         | ±25 | V    |
| Continuous total power dissipation                  |                        | See <a href="#">Dissipation Ratings</a> |     |      |
| Case temperature, $T_C$ , FK package (60 s)         |                        |                                         | 260 | °C   |
| Lead temperature <sup>(4)</sup>                     | D or N package (10 s)  |                                         | 260 | °C   |
|                                                     | J package (60 s)       |                                         | 300 |      |
| Storage temperature, $T_{stg}$                      |                        | –65                                     | 150 | °C   |

- (1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
- (2) All voltage values, except differential voltages, are with respect to the network ground terminal.
- (3) Differential voltage values are at the noninverting (A) input terminals with respect to the inverting (B) input terminals.
- (4) 1.6 mm (1/16 inch) from case

### 6.2 ESD Ratings

|                                     |                                                                                | VALUE | UNIT |
|-------------------------------------|--------------------------------------------------------------------------------|-------|------|
| $V_{(ESD)}$ Electrostatic discharge | Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001 <sup>(1)</sup>              | ±500  | V    |
|                                     | Charged-device model (CDM), per JEDEC specification JESD22-C101 <sup>(2)</sup> | ±2000 |      |

- (1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
- (2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

### 6.3 Recommended Operating Conditions

|                                      |                                    | MIN  | NOM | MAX  | UNIT |
|--------------------------------------|------------------------------------|------|-----|------|------|
| $V_{CC}$ Supply voltage              | AM26LS32AC, AM26LS32AI, AM26LS33AC | 4.75 | 5   | 5.25 | V    |
|                                      | AM26LS32AM, AM26LS33AM             | 4.5  | 5   | 5.5  |      |
| $V_{IH}$ High-level input voltage    |                                    | 2    |     |      | V    |
| $V_{IL}$ Low-level input voltage     |                                    |      |     | 0.8  | V    |
| $V_{IC}$ Common-mode input voltage   | AM26LS32A                          |      |     | ±7   | V    |
|                                      | AM26LS33A                          |      |     | ±15  |      |
| $I_{OH}$ High-level output current   |                                    |      |     | –440 | μA   |
| $I_{OL}$ Low-level output current    |                                    |      |     | 8    | mA   |
| $T_A$ Operating free-air temperature | AM26LS32AC, AM26LS33AC             | 0    |     | 70   | °C   |
|                                      | AM26LS32AI                         | –40  |     | 85   |      |
|                                      | AM26LS32AM, AM26LS33AM             | –55  |     | 125  |      |

## 6.4 Thermal Information

| THERMAL METRIC <sup>(1)</sup> |                                              | AM26LS3xAC, AM26LS32AI |          | AM26LS32AC |            | UNIT |
|-------------------------------|----------------------------------------------|------------------------|----------|------------|------------|------|
|                               |                                              | D (SOIC)               | N (PDIP) | NS (SO)    | PW (TSSOP) |      |
|                               |                                              | 16 PINS                | 16 PINS  | 16 PINS    | 16 PINS    |      |
| R <sub>θJA</sub>              | Junction-to-ambient thermal resistance       | 75.7                   | 45.3     | 75.8       | 102.7      | °C/W |
| R <sub>θJC(top)</sub>         | Junction-to-case (top) thermal resistance    | 35                     | 32.7     | 32.9       | 37.8       | °C/W |
| R <sub>θJB</sub>              | Junction-to-board thermal resistance         | 33.3                   | 25.3     | 36.6       | 47.7       | °C/W |
| ψ <sub>JT</sub>               | Junction-to-top characterization parameter   | 6.6                    | 17.8     | 6          | 3          | °C/W |
| ψ <sub>JB</sub>               | Junction-to-board characterization parameter | 33                     | 25.1     | 36.3       | 47.1       | °C/W |

- (1) For more information about traditional and new thermal metrics, see the [Semiconductor and IC Package Thermal Metrics](#) application report.

## 6.5 Electrical Characteristics

over recommended ranges of V<sub>CC</sub>, V<sub>IC</sub>, and operating free-air temperature (unless otherwise noted)

| PARAMETER          |                                                           | TEST CONDITIONS                                                                                    |                                    | MIN                 | TYP <sup>(1)</sup> | MAX   | UNIT |
|--------------------|-----------------------------------------------------------|----------------------------------------------------------------------------------------------------|------------------------------------|---------------------|--------------------|-------|------|
| V <sub>IT+</sub>   | Positive-going input threshold voltage                    | V <sub>O</sub> = V <sub>OHmin</sub> , I <sub>OH</sub> = –440 μA                                    | AM26LS32A                          |                     |                    | 0.2   | V    |
|                    |                                                           |                                                                                                    | AM26LS33A                          |                     |                    | 0.5   |      |
| V <sub>IT–</sub>   | Negative-going input threshold voltage                    | V <sub>O</sub> = 0.45 V, I <sub>OL</sub> = 8 mA                                                    | AM26LS32A                          | –0.2 <sup>(2)</sup> |                    |       | V    |
|                    |                                                           |                                                                                                    | AM26LS33A                          | –0.5 <sup>(2)</sup> |                    |       |      |
| V <sub>hys</sub>   | Hysteresis voltage (V <sub>IT+</sub> – V <sub>IT–</sub> ) |                                                                                                    |                                    |                     | 50                 |       | mV   |
| V <sub>IK</sub>    | Enable-input clamp voltage                                | V <sub>CC</sub> = MIN, I <sub>I</sub> = –18 mA                                                     |                                    |                     |                    | –1.5  | V    |
| V <sub>OH</sub>    | High-level output voltage                                 | V <sub>CC</sub> = MIN, V <sub>ID</sub> = 1 V, V <sub>I(G)</sub> = 0.8 V, I <sub>OH</sub> = –440 μA | AM26LS32AC, AM26LS33AC             |                     | 2.7                |       | V    |
|                    |                                                           |                                                                                                    | AM26LS32AM, AM26LS32AI, AM26LS33AM |                     | 2.5                |       |      |
| V <sub>OL</sub>    | Low-level output voltage                                  | V <sub>CC</sub> = MIN, V <sub>ID</sub> = –1 V, V <sub>I(G)</sub> = 0.8 V                           | I <sub>OL</sub> = 4 mA             |                     |                    | 0.4   | V    |
|                    |                                                           |                                                                                                    | I <sub>OL</sub> = 8 mA             |                     |                    | 0.45  |      |
| I <sub>OZ</sub>    | Off-state (high-impedance state) output current           | V <sub>CC</sub> = MAX                                                                              | V <sub>O</sub> = 2.4 V             |                     |                    | 20    | μA   |
|                    |                                                           |                                                                                                    | V <sub>O</sub> = 0.4 V             |                     |                    | –20   |      |
| I <sub>I</sub>     | Line input current                                        | V <sub>I</sub> = 15 V, other input at –10 V to 15 V                                                |                                    |                     |                    | 1.2   | mA   |
|                    |                                                           | V <sub>I</sub> = –15 V, other input at –15 V to 10 V                                               |                                    |                     |                    | –1.7  |      |
| I <sub>I(EN)</sub> | Enable input current                                      | V <sub>I</sub> = 5.5 V                                                                             |                                    |                     |                    | 100   | μA   |
| I <sub>H</sub>     | High-level enable current                                 | V <sub>I</sub> = 2.7 V                                                                             |                                    |                     |                    | 20    | μA   |
| I <sub>L</sub>     | Low-level enable current                                  | V <sub>I</sub> = 0.4 V                                                                             |                                    |                     |                    | –0.36 | mA   |
| r <sub>i</sub>     | Input resistance                                          | V <sub>IC</sub> = –15 V to 15 V, one input to ac ground                                            |                                    | 12                  | 15                 |       | kΩ   |
| I <sub>OS</sub>    | Short-circuit output current <sup>(3)</sup>               | V <sub>CC</sub> = MAX                                                                              |                                    | –15                 |                    | –85   | mA   |
| I <sub>CC</sub>    | Supply current                                            | V <sub>CC</sub> = MAX, all outputs disabled                                                        |                                    |                     | 52                 | 70    | mA   |

- (1) All typical values are at V<sub>CC</sub> = 5 V, T<sub>A</sub> = 25°C, and V<sub>IC</sub> = 0.  
(2) The algebraic convention, in which the less positive (more negative) limit is designated as minimum, is used in this data sheet for threshold levels only.  
(3) Not more than one output must be shorted to ground at a time, and duration of the short circuit must not exceed one second.

## 6.6 Switching Characteristics

$C_L = 15$  pF,  $V_{CC} = 5$  V, and  $T_A = 25^\circ\text{C}$  (see [Parameter Measurement Information](#); unless otherwise noted)


| PARAMETER                                                  | MIN | TYP <sup>(1)</sup> | MAX | UNIT |
|------------------------------------------------------------|-----|--------------------|-----|------|
| $t_{PLH}$ Propagation delay time, low-to-high-level output |     | 20                 | 35  | ns   |
| $t_{PHL}$ Propagation delay time, high-to-low-level output |     | 22                 | 35  | ns   |
| $t_{PZH}$ Output enable time to high level                 |     | 17                 | 22  | ns   |
| $t_{PZL}$ Output enable time to low level                  |     | 20                 | 25  | ns   |
| $t_{PHZ}$ Output disable time from high level              |     | 21                 | 30  | ns   |
| $t_{PLZ}$ Output disable time from low level               |     | 30                 | 40  | ns   |

(1) All typical values are at  $V_{CC} = 5$  V,  $T_A = 25^\circ\text{C}$ , and  $V_{IC} = 0$ .

## 6.7 Dissipation Ratings


| PACKAGE | $T_A \leq 25^\circ\text{C}$<br>POWER RATING | DERATION FACTOR<br>ABOVE $T_A = 25^\circ\text{C}$ | $T_A = 70^\circ\text{C}$<br>POWER RATING | $T_A = 125^\circ\text{C}$<br>POWER RATING |
|---------|---------------------------------------------|---------------------------------------------------|------------------------------------------|-------------------------------------------|
| FK      | 1375 mW                                     | 11 mW/ $^\circ\text{C}$                           | 880 mW                                   | 275 mW                                    |
| J       | 1375 mW                                     | 11 mW/ $^\circ\text{C}$                           | 880 mW                                   | 275 mW                                    |

## 6.8 Typical Characteristics




†  $V_{CC} = 5.5\text{ V}$  and  $V_{CC} = 4.5\text{ V}$  applies to M-suffix devices only.


**Figure 1. High-Level Output Voltage vs High-Level Output Current**




**Figure 2. Low-Level Output Voltage vs Low-Level Output Current**




**Figure 3. Low-Level Output Voltage vs Free-Air Temperature**



**Figure 4. Output Voltage vs Enable G Voltage**



**Figure 5. Output Voltage vs Enable G Voltage**



**Figure 6. Output Voltage vs Enable G Voltage**

## Typical Characteristics (continued)




Figure 7. Output Voltage vs Enable G Voltage




Figure 8. AM26LS32A Output Voltage vs Differential Input Voltage





Figure 9. AM26LS33A Output Voltage vs Differential Input Voltage



The unshaded area shows requirements of paragraph 4.2.1 of ANSI Standards EIA/TIA-422-B and EIA/TIA-423-B.

Figure 10. Input Current vs Input Voltage



## 7 Parameter Measurement Information




Figure 11. Test Circuit




Figure 12. Voltage Waveforms For  $t_{PLH}$ ,  $t_{PHL}$






Figure 13. Voltage Waveforms For  $t_{PHZ}$ ,  $t_{PZH}$

## Parameter Measurement Information (continued)



- A. CL includes probe and jig capacitance.
- B. All diodes are 1N3064 or equivalent.
- C. Enable G is tested with  $\bar{G}$  high,  $\bar{G}$  is tested with G low.

Figure 14. Voltage Waveforms For  $t_{PLZ}$ ,  $t_{PZL}$



Copyright © 2016, Texas Instruments Incorporated


Figure 15. Schematics of Inputs and Outputs

## 8 Detailed Description

### 8.1 Overview

The AM26LS32 is a quadruple-differential line receiver that meets the necessary requirements for NSI TIA/EIA-422-B, TIA/EIA-423-B, and ITU Recommendation V.10 and V.11. This device allows a low-power or low-voltage MCU to interface with heavy machinery, subsystems, and other devices through long wires of up to 1000 m, giving any design a reliable and easy-to-use connection. As any RS422 interface, the AM26LS32 works in a differential voltage range, which enables very good signal integrity.

### 8.2 Functional Block Diagram



Copyright © 2016, Texas Instruments Incorporated

**Figure 16. Logic Diagram (Positive Logic)**

### 8.3 Feature Description

The device can be configured using the G and  $\overline{G}$  logic inputs to select receiver output. The high voltage or logic 1 on the G pin allows the device to operate on an active-high, and having a low voltage or logic 0 on the  $\overline{G}$  enables active low operation. These are simple ways to configure the logic to match that of the receiving or transmitting controller or microprocessor.

### 8.4 Device Functional Modes

The receivers implemented in these RS422 devices can be configured using the G and  $\overline{G}$  logic pins to be enabled or disabled. This allows users to ignore or filter out transmissions as desired.

**Table 1. Function Table, Each Receiver**

| DIFFERENTIAL<br>A–B                | ENABLES <sup>(1)</sup> |                | OUTPUT <sup>(1)</sup><br>Y |
|------------------------------------|------------------------|----------------|----------------------------|
|                                    | G                      | $\overline{G}$ |                            |
| $V_{ID} \geq V_{IT+}$              | H                      | X              | H                          |
|                                    | X                      | L              | H                          |
| $V_{IT-} \leq V_{ID} \leq V_{IT+}$ | H                      | X              | ?                          |
|                                    | X                      | L              | ?                          |
| $V_{ID} \leq V_{IT-}$              | H                      | X              | L                          |
|                                    | X                      | L              | L                          |
| X                                  | L                      | H              | Z                          |
| Open                               | H                      | X              | H                          |
|                                    | X                      | L              | H                          |

(1) H = High level, L = Low level, X = Irrelevant, Z = High impedance (off), ? = Indeterminate

## 9 Application and Implementation

### NOTE


Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

### 9.1 Application Information

When using AM26LS32A as a receiver, the AM26LS31AC can allow multiple AM26LS32As to be used causing an increase in the amount of outputs.

### 9.2 Typical Application

Figure 17 shows a configuration with no termination. Although reflections are present at the receiver inputs at a data signaling rate of 200 kbps with no termination, the RS-422-compliant receiver reads only the input differential voltage and produces a clean signal at the output.



<sup>†</sup>R<sub>T</sub> equals the characteristic impedance of the line.

Figure 17. Application Diagram

#### 9.2.1 Design Requirements


Resistor and capacitor (if used) termination values are shown for each laboratory experiment, but vary from system to system. For example, the termination resistor, R<sub>T</sub>, must be within 20% of the characteristic impedance, Z<sub>O</sub>, of the cable and can vary from about 80 Ω to 120 Ω.

#### 9.2.2 Detailed Design Procedure

Add a V<sub>CC</sub> bypass capacitor (0.1 μF or more). Either enable (G pin) input can turn on the receivers, so connect the desired enable to a compatible logic line output. The other enable input must be tied to the inactive state supply rail. If the receivers must always be active, then connect both enables to the supply rail such that at least one is set to an active-state rail. V<sub>CC</sub> must be 5 V within 10% and logic inputs must provide TTL-compatible voltage levels A & B Inputs can lead to an external connector or can be left unconnected. The last receiver on a cable requires termination, either on-board or use as an external resistor. Unused Y outputs can be left unconnected.

## Typical Application (continued)

### 9.2.3 Application Curve



**Figure 18. High-Level Output Voltage vs Free-Air Temperature**

## 10 Power Supply Recommendations

Place 0.1- $\mu$ F bypass capacitors close to the power-supply pins to reduce errors coupling in from noisy or high-impedance power supplies.

## 11 Layout

### 11.1 Layout Guidelines

For best operational performance of the device, use good PCB layout practices including:

- Noise can propagate into analog circuitry through the power pins of the circuit as a whole, as well as the operational amplifier. Bypass capacitors are used to reduce the coupled noise by providing low impedance power sources local to the analog circuitry.
- Connect low-ESR, 0.1- $\mu$ F ceramic bypass capacitors between each supply pin and ground, placed as close to the device as possible. A single bypass capacitor from V+ to ground is applicable for single supply applications.
- Separate grounding for analog and digital portions of circuitry is one of the simplest and most-effective methods of noise suppression. One or more layers on multilayer PCBs are usually devoted to ground planes. A ground plane helps distribute heat and reduces EMI noise pickup. Make sure to physically separate digital and analog grounds, paying attention to the flow of the ground current.
- To reduce parasitic coupling, run the input traces as far away from the supply or output traces as possible. If it is not possible to keep them separate, it is much better to cross the sensitive trace perpendicular as opposed to in parallel with the noisy trace.
- Place the external components as close to the device as possible. Keeping RF and RG close to the inverting input minimizes parasitic capacitance.
- Keep the length of input traces as short as possible. Always remember that the input traces are the most sensitive part of the circuit.
- Consider a driven, low-impedance guard ring around the critical traces. A guard ring can significantly reduce leakage currents from nearby traces that are at different potentials.

## 11.2 Layout Example




Figure 19. Layout with PCB Recommendations

## 12 Device and Documentation Support

### 12.1 Related Links

The table below lists quick access links. Categories include technical documents, support and community resources, tools and software, and quick access to sample or buy.

**Table 2. Related Links**

| PARTS      | PRODUCT FOLDER             | SAMPLE & BUY               | TECHNICAL DOCUMENTS        | TOOLS & SOFTWARE           | SUPPORT & COMMUNITY        |
|------------|----------------------------|----------------------------|----------------------------|----------------------------|----------------------------|
| AM26LS32AC | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> |
| AM26LS32AI | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> |
| AM26LS32AM | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> |
| AM26LS33AC | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> |
| AM26LS33AM | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> |

### 12.2 Receiving Notification of Documentation Updates

To receive notification of documentation updates, navigate to the device product folder on ti.com. In the upper right corner, click on *Alert me* to register and receive a weekly digest of any product information that has changed. For change details, review the revision history included in any revised document.

### 12.3 Community Resources

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's [Terms of Use](#).

**TI E2E™ Online Community** *TI's Engineer-to-Engineer (E2E) Community*. Created to foster collaboration among engineers. At e2e.ti.com, you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

**Design Support** *TI's Design Support* Quickly find helpful E2E forums along with design support tools and contact information for technical support.

### 12.4 Trademarks

E2E is a trademark of Texas Instruments.  
All other trademarks are the property of their respective owners.

### 12.5 Electrostatic Discharge Caution



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

### 12.6 Glossary

[SLYZ022](#) — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

## 13 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

**PACKAGING INFORMATION**

| Orderable Device | Status<br>(1) | Package Type | Package<br>Drawing | Pins | Package<br>Qty | Eco Plan<br>(2)            | Lead/Ball Finish<br>(6) | MSL Peak Temp<br>(3) | Op Temp (°C) | Device Marking<br>(4/5)                  | Samples                 |
|------------------|---------------|--------------|--------------------|------|----------------|----------------------------|-------------------------|----------------------|--------------|------------------------------------------|-------------------------|
| 5962-7802003M2A  | ACTIVE        | LCCC         | FK                 | 20   | 1              | TBD                        | POST-PLATE              | N / A for Pkg Type   | -55 to 125   | 5962-<br>7802003M2A<br>AM26LS<br>32AMFKB | <a href="#">Samples</a> |
| 5962-7802003MEA  | ACTIVE        | CDIP         | J                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | 5962-7802003ME<br>A<br>AM26LS32AMJB      | <a href="#">Samples</a> |
| 5962-7802003MFA  | ACTIVE        | CFP          | W                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | 5962-7802003MF<br>A<br>AM26LS32AMWB      | <a href="#">Samples</a> |
| 5962-7802004M2A  | ACTIVE        | LCCC         | FK                 | 20   | 1              | TBD                        | POST-PLATE              | N / A for Pkg Type   | -55 to 125   | 5962-<br>7802004M2A<br>AM26LS<br>33AMFKB | <a href="#">Samples</a> |
| 5962-7802004MEA  | ACTIVE        | CDIP         | J                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | 5962-7802004ME<br>A<br>AM26LS33AMJB      | <a href="#">Samples</a> |
| 5962-7802004MFA  | ACTIVE        | CFP          | W                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | 5962-7802004MF<br>A<br>AM26LS33AMWB      | <a href="#">Samples</a> |
| AM26LS32ACD      | ACTIVE        | SOIC         | D                  | 16   | 40             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS32AC                                 | <a href="#">Samples</a> |
| AM26LS32ACDE4    | ACTIVE        | SOIC         | D                  | 16   | 40             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS32AC                                 | <a href="#">Samples</a> |
| AM26LS32ACDG4    | ACTIVE        | SOIC         | D                  | 16   | 40             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS32AC                                 | <a href="#">Samples</a> |
| AM26LS32ACDR     | ACTIVE        | SOIC         | D                  | 16   | 2500           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS32AC                                 | <a href="#">Samples</a> |
| AM26LS32ACDRE4   | ACTIVE        | SOIC         | D                  | 16   | 2500           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS32AC                                 | <a href="#">Samples</a> |
| AM26LS32ACDRG4   | ACTIVE        | SOIC         | D                  | 16   | 2500           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS32AC                                 | <a href="#">Samples</a> |
| AM26LS32ACN      | ACTIVE        | PDIP         | N                  | 16   | 25             | Pb-Free<br>(RoHS)          | CU NIPDAU               | N / A for Pkg Type   | 0 to 70      | AM26LS32ACN                              | <a href="#">Samples</a> |



| Orderable Device | Status<br>(1) | Package Type | Package<br>Drawing | Pins | Package<br>Qty | Eco Plan<br>(2)            | Lead/Ball Finish<br>(6) | MSL Peak Temp<br>(3) | Op Temp (°C) | Device Marking<br>(4/5)                  | Samples                 |
|------------------|---------------|--------------|--------------------|------|----------------|----------------------------|-------------------------|----------------------|--------------|------------------------------------------|-------------------------|
| AM26LS32ACNE4    | ACTIVE        | PDIP         | N                  | 16   | 25             | Pb-Free<br>(RoHS)          | CU NIPDAU               | N / A for Pkg Type   | 0 to 70      | AM26LS32ACN                              | <a href="#">Samples</a> |
| AM26LS32ACNSR    | ACTIVE        | SO           | NS                 | 16   | 2000           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS32A                                  | <a href="#">Samples</a> |
| AM26LS32ACNSRG4  | ACTIVE        | SO           | NS                 | 16   | 2000           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS32A                                  | <a href="#">Samples</a> |
| AM26LS32ACPW     | ACTIVE        | TSSOP        | PW                 | 16   | 90             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | SA32A                                    | <a href="#">Samples</a> |
| AM26LS32ACPWE4   | ACTIVE        | TSSOP        | PW                 | 16   | 90             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | SA32A                                    | <a href="#">Samples</a> |
| AM26LS32ACPWR    | ACTIVE        | TSSOP        | PW                 | 16   | 2000           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | SA32A                                    | <a href="#">Samples</a> |
| AM26LS32ACPWRE4  | ACTIVE        | TSSOP        | PW                 | 16   | 2000           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | SA32A                                    | <a href="#">Samples</a> |
| AM26LS32ACPWRG4  | ACTIVE        | TSSOP        | PW                 | 16   | 2000           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | SA32A                                    | <a href="#">Samples</a> |
| AM26LS32AID      | ACTIVE        | SOIC         | D                  | 16   | 40             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | -40 to 85    | 26LS32AI                                 | <a href="#">Samples</a> |
| AM26LS32AIDE4    | ACTIVE        | SOIC         | D                  | 16   | 40             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | -40 to 85    | 26LS32AI                                 | <a href="#">Samples</a> |
| AM26LS32AIDG4    | ACTIVE        | SOIC         | D                  | 16   | 40             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | -40 to 85    | 26LS32AI                                 | <a href="#">Samples</a> |
| AM26LS32AIDR     | ACTIVE        | SOIC         | D                  | 16   | 2500           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | -40 to 85    | 26LS32AI                                 | <a href="#">Samples</a> |
| AM26LS32AIDRG4   | ACTIVE        | SOIC         | D                  | 16   | 2500           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | -40 to 85    | 26LS32AI                                 | <a href="#">Samples</a> |
| AM26LS32AIN      | ACTIVE        | PDIP         | N                  | 16   | 25             | Pb-Free<br>(RoHS)          | CU NIPDAU               | N / A for Pkg Type   | -40 to 85    | AM26LS32AIN                              | <a href="#">Samples</a> |
| AM26LS32AINE4    | ACTIVE        | PDIP         | N                  | 16   | 25             | Pb-Free<br>(RoHS)          | CU NIPDAU               | N / A for Pkg Type   | -40 to 85    | AM26LS32AIN                              | <a href="#">Samples</a> |
| AM26LS32AMFKB    | ACTIVE        | LCCC         | FK                 | 20   | 1              | TBD                        | POST-PLATE              | N / A for Pkg Type   | -55 to 125   | 5962-<br>7802003M2A<br>AM26LS<br>32AMFKB | <a href="#">Samples</a> |
| AM26LS32AMJ      | ACTIVE        | CDIP         | J                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | AM26LS32AMJ                              | <a href="#">Samples</a> |

| Orderable Device | Status<br>(1) | Package Type | Package<br>Drawing | Pins | Package<br>Qty | Eco Plan<br>(2)            | Lead/Ball Finish<br>(6) | MSL Peak Temp<br>(3) | Op Temp (°C) | Device Marking<br>(4/5)                  | Samples                 |
|------------------|---------------|--------------|--------------------|------|----------------|----------------------------|-------------------------|----------------------|--------------|------------------------------------------|-------------------------|
| AM26LS32AMJB     | ACTIVE        | CDIP         | J                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | 5962-7802003ME<br>A<br>AM26LS32AMJB      | <a href="#">Samples</a> |
| AM26LS32AMWB     | ACTIVE        | CFP          | W                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | 5962-7802003MF<br>A<br>AM26LS32AMWB      | <a href="#">Samples</a> |
| AM26LS33ACD      | ACTIVE        | SOIC         | D                  | 16   | 40             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS33AC                                 | <a href="#">Samples</a> |
| AM26LS33ACDG4    | ACTIVE        | SOIC         | D                  | 16   | 40             | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS33AC                                 | <a href="#">Samples</a> |
| AM26LS33ACDR     | ACTIVE        | SOIC         | D                  | 16   | 2500           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS33AC                                 | <a href="#">Samples</a> |
| AM26LS33ACDRE4   | ACTIVE        | SOIC         | D                  | 16   | 2500           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS33AC                                 | <a href="#">Samples</a> |
| AM26LS33ACDRG4   | ACTIVE        | SOIC         | D                  | 16   | 2500           | Green (RoHS<br>& no Sb/Br) | CU NIPDAU               | Level-1-260C-UNLIM   | 0 to 70      | 26LS33AC                                 | <a href="#">Samples</a> |
| AM26LS33ACN      | ACTIVE        | PDIP         | N                  | 16   | 25             | Pb-Free<br>(RoHS)          | CU NIPDAU               | N / A for Pkg Type   | 0 to 70      | AM26LS33ACN                              | <a href="#">Samples</a> |
| AM26LS33ACNE4    | ACTIVE        | PDIP         | N                  | 16   | 25             | Pb-Free<br>(RoHS)          | CU NIPDAU               | N / A for Pkg Type   | 0 to 70      | AM26LS33ACN                              | <a href="#">Samples</a> |
| AM26LS33AMFKB    | ACTIVE        | LCCC         | FK                 | 20   | 1              | TBD                        | POST-PLATE              | N / A for Pkg Type   | -55 to 125   | 5962-<br>7802004M2A<br>AM26LS<br>33AMFKB | <a href="#">Samples</a> |
| AM26LS33AMJ      | ACTIVE        | CDIP         | J                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | AM26LS33AMJ                              | <a href="#">Samples</a> |
| AM26LS33AMJB     | ACTIVE        | CDIP         | J                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | 5962-7802004ME<br>A<br>AM26LS33AMJB      | <a href="#">Samples</a> |
| AM26LS33AMWB     | ACTIVE        | CFP          | W                  | 16   | 1              | TBD                        | A42                     | N / A for Pkg Type   | -55 to 125   | 5962-7802004MF<br>A<br>AM26LS33AMWB      | <a href="#">Samples</a> |

<sup>(1)</sup> The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

**NRND:** Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW:** Device has been announced but is not in production. Samples may or may not be available.

---

**OBSOLETE:** TI has discontinued the production of the device.

<sup>(2)</sup> Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

**TBD:** The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

**Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

**Green (RoHS & no Sb/Br):** TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

<sup>(3)</sup> MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

<sup>(4)</sup> There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

<sup>(5)</sup> Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

<sup>(6)</sup> Lead/Ball Finish - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead/Ball Finish values may wrap to two lines if the finish value exceeds the maximum column width.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.


In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

**OTHER QUALIFIED VERSIONS OF AM26LS32A, AM26LS32AM, AM26LS33A, AM26LS33AM :**

- Catalog: [AM26LS32A](#), [AM26LS33A](#)
- Military: [AM26LS32AM](#), [AM26LS33AM](#)
- Space: [AM26LS33A-SP](#), [AM26LS33A-SP](#)

NOTE: Qualified Version Definitions:


- Catalog - TI's standard catalog product
- Military - QML certified for Military and Defense Applications
- Space - Radiation tolerant, ceramic packaging and qualified for use in Space-based application

**TAPE AND REEL INFORMATION**


\*All dimensions are nominal

| Device        | Package Type | Package Drawing | Pins | SPQ  | Reel Diameter (mm) | Reel Width W1 (mm) | A0 (mm) | B0 (mm) | K0 (mm) | P1 (mm) | W (mm) | Pin1 Quadrant |
|---------------|--------------|-----------------|------|------|--------------------|--------------------|---------|---------|---------|---------|--------|---------------|
| AM26LS32ACDR  | SOIC         | D               | 16   | 2500 | 330.0              | 16.4               | 6.5     | 10.3    | 2.1     | 8.0     | 16.0   | Q1            |
| AM26LS32ACDR  | SOIC         | D               | 16   | 2500 | 330.0              | 16.4               | 6.5     | 10.3    | 2.1     | 8.0     | 16.0   | Q1            |
| AM26LS32ACPWR | TSSOP        | PW              | 16   | 2000 | 330.0              | 12.4               | 6.9     | 5.6     | 1.6     | 8.0     | 12.0   | Q1            |
| AM26LS32AIDR  | SOIC         | D               | 16   | 2500 | 330.0              | 16.4               | 6.5     | 10.3    | 2.1     | 8.0     | 16.0   | Q1            |
| AM26LS33ACDR  | SOIC         | D               | 16   | 2500 | 330.0              | 16.4               | 6.5     | 10.3    | 2.1     | 8.0     | 16.0   | Q1            |

## TAPE AND REEL BOX DIMENSIONS




\*All dimensions are nominal

| Device        | Package Type | Package Drawing | Pins | SPQ  | Length (mm) | Width (mm) | Height (mm) |
|---------------|--------------|-----------------|------|------|-------------|------------|-------------|
| AM26LS32ACDR  | SOIC         | D               | 16   | 2500 | 367.0       | 367.0      | 38.0        |
| AM26LS32ACDR  | SOIC         | D               | 16   | 2500 | 333.2       | 345.9      | 28.6        |
| AM26LS32ACPWR | TSSOP        | PW              | 16   | 2000 | 367.0       | 367.0      | 35.0        |
| AM26LS32AIDR  | SOIC         | D               | 16   | 2500 | 333.2       | 345.9      | 28.6        |
| AM26LS33ACDR  | SOIC         | D               | 16   | 2500 | 333.2       | 345.9      | 28.6        |



FK (S-CQCC-N\*\*)

LEADLESS CERAMIC CHIP CARRIER

28 TERMINAL SHOWN



| NO. OF<br>TERMINALS<br>** | A                |                  | B                |                  |
|---------------------------|------------------|------------------|------------------|------------------|
|                           | MIN              | MAX              | MIN              | MAX              |
| 20                        | 0.342<br>(8,69)  | 0.358<br>(9,09)  | 0.307<br>(7,80)  | 0.358<br>(9,09)  |
| 28                        | 0.442<br>(11,23) | 0.458<br>(11,63) | 0.406<br>(10,31) | 0.458<br>(11,63) |
| 44                        | 0.640<br>(16,26) | 0.660<br>(16,76) | 0.495<br>(12,58) | 0.560<br>(14,22) |
| 52                        | 0.740<br>(18,78) | 0.761<br>(19,32) | 0.495<br>(12,58) | 0.560<br>(14,22) |
| 68                        | 0.938<br>(23,83) | 0.962<br>(24,43) | 0.850<br>(21,6)  | 0.858<br>(21,8)  |
| 84                        | 1.141<br>(28,99) | 1.165<br>(29,59) | 1.047<br>(26,6)  | 1.063<br>(27,0)  |




4040140/D 01/11

- NOTES:
- All linear dimensions are in inches (millimeters).
  - This drawing is subject to change without notice.
  - This package can be hermetically sealed with a metal lid.
  - Falls within JEDEC MS-004

D (R-PDSO-G16)

PLASTIC SMALL OUTLINE




4040047-6/M 06/11

- NOTES:
- A. All linear dimensions are in inches (millimeters).
  - B. This drawing is subject to change without notice.
  - C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
  - D. Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
  - E. Reference JEDEC MS-012 variation AC.



D (R-PDSO-G16)

PLASTIC SMALL OUTLINE




- NOTES:
- A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Publication IPC-7351 is recommended for alternate designs.
  - D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC-7525 for other stencil recommendations.
  - E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.

# MECHANICAL DATA

NS (R-PDSO-G\*\*)

PLASTIC SMALL-OUTLINE PACKAGE

14-PINS SHOWN




| DIM \ PINS ** | 14    | 16    | 20    | 24    |
|---------------|-------|-------|-------|-------|
| A MAX         | 10,50 | 10,50 | 12,90 | 15,30 |
| A MIN         | 9,90  | 9,90  | 12,30 | 14,70 |

4040062/C 03/03

- NOTES:
- A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Body dimensions do not include mold flash or protrusion, not to exceed 0,15.

W (R-GDFP-F16)

CERAMIC DUAL FLATPACK




- NOTES:
- All linear dimensions are in inches (millimeters).
  - This drawing is subject to change without notice.
  - This package can be hermetically sealed with a ceramic lid using glass frit.
  - Index point is provided on cap for terminal identification only.
  - Falls within MIL STD 1835 GDFP2-F16


J (R-GDIP-T\*\*)

14 LEADS SHOWN

# CERAMIC DUAL IN-LINE PACKAGE



| PINS **<br>DIM | 14                     | 16                     | 18                     | 20                     |
|----------------|------------------------|------------------------|------------------------|------------------------|
| A              | 0.300<br>(7,62)<br>BSC | 0.300<br>(7,62)<br>BSC | 0.300<br>(7,62)<br>BSC | 0.300<br>(7,62)<br>BSC |
| B MAX          | 0.785<br>(19,94)       | .840<br>(21,34)        | 0.960<br>(24,38)       | 1.060<br>(26,92)       |
| B MIN          | —                      | —                      | —                      | —                      |
| C MAX          | 0.300<br>(7,62)        | 0.300<br>(7,62)        | 0.310<br>(7,87)        | 0.300<br>(7,62)        |
| C MIN          | 0.245<br>(6,22)        | 0.245<br>(6,22)        | 0.220<br>(5,59)        | 0.245<br>(6,22)        |




4040083/F 03/03

- NOTES:
- A. All linear dimensions are in inches (millimeters).
  - B. This drawing is subject to change without notice.
  - C. This package is hermetically sealed with a ceramic lid using glass frit.
  - D. Index point is provided on cap for terminal identification only on press ceramic glass frit seal only.
  - E. Falls within MIL STD 1835 GDIP1-T14, GDIP1-T16, GDIP1-T18 and GDIP1-T20.

PW (R-PDSO-G16)


PLASTIC SMALL OUTLINE



- NOTES:
- A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
  - B. This drawing is subject to change without notice.
  - C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0,15 each side.
  - D. Body width does not include interlead flash. Interlead flash shall not exceed 0,25 each side.
  - E. Falls within JEDEC MO-153

PW (R-PDSO-G16)

PLASTIC SMALL OUTLINE




- NOTES:
- A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Publication IPC-7351 is recommended for alternate designs.
  - D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC-7525 for other stencil recommendations.
  - E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.


## N (R-PDIP-T\*\*)

16 PINS SHOWN

## PLASTIC DUAL-IN-LINE PACKAGE



| PINS **             | 14               | 16               | 18               | 20               |
|---------------------|------------------|------------------|------------------|------------------|
| DIM                 |                  |                  |                  |                  |
| A MAX               | 0.775<br>(19,69) | 0.775<br>(19,69) | 0.920<br>(23,37) | 1.060<br>(26,92) |
| A MIN               | 0.745<br>(18,92) | 0.745<br>(18,92) | 0.850<br>(21,59) | 0.940<br>(23,88) |
| MS-001<br>VARIATION | AA               | BB               | AC               | AD               |



14/18 Pin Only  
20 Pin vendor option

4040049/E 12/2002

- NOTES:
- A. All linear dimensions are in inches (millimeters).
  - B. This drawing is subject to change without notice.
  - Falls within JEDEC MS-001, except 18 and 20 pin minimum body length (Dim A).
  - The 20 pin end lead shoulder width is a vendor option, either half or full width.

## IMPORTANT NOTICE

Texas Instruments Incorporated (TI) reserves the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

TI's published terms of sale for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>) apply to the sale of packaged integrated circuit products that TI has qualified and released to market. Additional terms may apply to the use or sale of other types of TI products and services.

Reproduction of significant portions of TI information in TI data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such reproduced documentation. Information of third parties may be subject to additional restrictions. Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyers and others who are developing systems that incorporate TI products (collectively, "Designers") understand and agree that Designers remain responsible for using their independent analysis, evaluation and judgment in designing their applications and that Designers have full and exclusive responsibility to assure the safety of Designers' applications and compliance of their applications (and of all TI products used in or for Designers' applications) with all applicable regulations, laws and other applicable requirements. Designer represents that, with respect to their applications, Designer has all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. Designer agrees that prior to using or distributing any applications that include TI products, Designer will thoroughly test such applications and the functionality of such TI products as used in such applications.

TI's provision of technical, application or other design advice, quality characterization, reliability data or other services or information, including, but not limited to, reference designs and materials relating to evaluation modules, (collectively, "TI Resources") are intended to assist designers who are developing applications that incorporate TI products; by downloading, accessing or using TI Resources in any way, Designer (individually or, if Designer is acting on behalf of a company, Designer's company) agrees to use any particular TI Resource solely for this purpose and subject to the terms of this Notice.

TI's provision of TI Resources does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such TI Resources. TI reserves the right to make corrections, enhancements, improvements and other changes to its TI Resources. TI has not conducted any testing other than that specifically described in the published documentation for a particular TI Resource.

Designer is authorized to use, copy and modify any individual TI Resource only in connection with the development of applications that include the TI product(s) identified in such TI Resource. NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information regarding or referencing third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of TI Resources may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI RESOURCES ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING RESOURCES OR USE THEREOF, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS. TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY DESIGNER AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS EVEN IF DESCRIBED IN TI RESOURCES OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF TI RESOURCES OR USE THEREOF, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Unless TI has explicitly designated an individual product as meeting the requirements of a particular industry standard (e.g., ISO/TS 16949 and ISO 26262), TI is not responsible for any failure to meet such industry standard requirements.

Where TI specifically promotes products as facilitating functional safety or as compliant with industry functional safety standards, such products are intended to help enable customers to design and create their own applications that meet applicable functional safety standards and requirements. Using products in an application does not by itself establish any safety features in the application. Designers must ensure compliance with safety-related requirements and standards applicable to their applications. Designer may not use any TI products in life-critical medical equipment unless authorized officers of the parties have executed a special contract specifically governing such use. Life-critical medical equipment is medical equipment where failure of such equipment would cause serious bodily injury or death (e.g., life support, pacemakers, defibrillators, heart pumps, neurostimulators, and implantables). Such equipment includes, without limitation, all medical devices identified by the U.S. Food and Drug Administration as Class III devices and equivalent classifications outside the U.S.

TI may expressly designate certain products as completing a particular qualification (e.g., Q100, Military Grade, or Enhanced Product). Designers agree that it has the necessary expertise to select the product with the appropriate qualification designation for their applications and that proper product selection is at Designers' own risk. Designers are solely responsible for compliance with all legal and regulatory requirements in connection with such selection.

Designer will fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of Designer's non-compliance with the terms and provisions of this Notice.



# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Texas Instruments:

[AM26LS32ACDR](#) [AM26LS32ACD](#) [AM26LS32ACN](#) [AM26LS32ACNSR](#) [AM26LS32ACDG4](#) [AM26LS32ACDRG4](#)  
[AM26LS32ACDE4](#) [AM26LS32ACDRE4](#) [AM26LS32ACNE4](#) [AM26LS32ACNSRG4](#) [AM26LS32ACPW](#)  
[AM26LS32ACPWE4](#) [AM26LS32ACPWR](#) [AM26LS32ACPWRE4](#) [AM26LS32ACPWRG4](#)