

Manual Switches

Lighted Indicators

AML41/42 Series

To order lamps see page 58.

FEATURES

- Pushbutton style indicators match display of standard bezel lighted switches. Choice of incandescent or LED illumination.
- Lens style indicators use a special cap-like button which covers the bezel to present a larger display area, without affecting family appearance. Up to 3-lamp split screen capability. Incandescent illumination.



AML41
(Use AML51 push-buttons only. Page 42.)



AML41
(Use AML51-J/-K/-L lens buttons only. Page 42.)

AML41 INCANDESCENT DISPLAY INDICATORS ORDER GUIDE

AML41 C		B	A	2
Housing Type		Bezel Color	Incand. Lamp Type	Terminal Type
Pushbutton Style:	Lens Style:			
AML41 C Square 1 lamp ckt.	AML41 J Rectangular 1 lamp ckt.	B Black	A No lamp installed	2 .110 × .020 (Solder or Quick-Connect)
AML41 D Square 2 lamp ckts.	AML41 K Rectangular 2 lamp ckts.		B 6 V Lamp*	3 .025 × .025 (Printed Circuit or Push-On)
AML41 F Rectangular 1 lamp ckt.	AML41 L Rectangular 3 lamp ckts.		C 14 V Lamp*	
AML41 G Rectangular 2 lamp ckts.			E 28 V Lamp*	

* Lamps will be installed per each lamp circuit specified in the Housing Type.

Examples:

AML41CBA2
Square (pushbutton style) indicator housing with one lamp circuit; black bezel; .110 × .020 termination.

AML41JBA2
Rectangular (lens style) indicator housing with one lamp circuit; black bezel; .110 × .020 termination.



AML42C
(Use AML52-C/-A pushbuttons only. Page 43.)



AML42S

AML42 LED DISPLAY INDICATORS ORDER GUIDE

LEDs are not replaceable.

AML42 S	B	C	2
Housing Type	Bezel Color	LED Color/Voltage	Terminal Type/ Diode Protection
AML42 C Square 1 LED	B Black	Red B V* C 5 V D 10 V E 15 V F 24 V	2 .110 × .020 (Solder or Q.C.)
AML42 S Compact 1 LED	Yellow H V* J 5 V K 10 V L 15 V M 24 V	Green R V* S 5 V T 10 V W 15 V X 24 V	3 .025 × .025 (Printed Circuit or Push-On)
			8 .110 × .020 w/diode to protect LED
			9 .025 × .025 w/diode to protect LED

Example: **AML42SBC2**
Compact indicator with black bezel; 5 volt red LED; .110 × .020 termination.

* See LED application data, page 58, for these devices without current-limiting resistor.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Honeywell:

[AML41FBC2-006](#) [AML41JBA2-001](#) [AML42CBJ8](#) [AML41CBA2](#) [AML41FBA2](#) [AML41CBE2](#) [AML41CBE3](#)
[AML41DBA2](#) [AML41GBA2](#) [AML41GBE2](#) [AML41JBA3](#) [AML42CBB2](#) [AML42CBC8](#) [AML42CBE2](#) [AML42CBF2](#)
[AML42CBF8](#) [AML42CBH2](#) [AML42CBM2](#) [AML42CBS2](#) [AML42CBS2-001](#) [AML42CBX2](#) [AML42SBB2](#) [AML42SBB3](#)
[AML42SBE2](#) [AML42SBF3](#) [AML42SBF8](#) [AML42SBH2](#) [AML42SBL2](#) [AML42SBL8](#) [AML42SBM2](#) [AML42SBM3](#)
[AML42SBR2](#) [AML42SBR3](#) [AML42SBW2](#) [AML42SBX3](#) [AML41JBA2](#) [AML41DBE2](#) [AML42SBW8-001](#) [AML42SBS8](#)
[AML41LBA2](#) [AML41KBE2](#) [AML41FBE2](#)