



BC183,L · BC213,L


COMPLEMENTARY SILICON AF SMALL SIGNAL AMPLIFIERS & DRIVERS

The BC183, BC183L (NPN) & BC213, BC213L (PNP) are complementary silicon planar epitaxial transistors for use in AF small signal amplifiers and drivers, as well as for low power universal applications. Both types feature good linearity of D.C. current gain.

TO-92B



ECB



BC184L
BC214L

BC184
BC214

ABSOLUTE MAXIMUM RATINGS

		BC183,L	BC213,L
Collector-Base Voltage	V_{CB0}	45V	45V
Collector-Emitter Voltage	V_{CE0}	30V	30V
Emitter-Base Voltage	V_{EB0}	6V	5V
Collector Current	I_C		200mA
Total Power Dissipation @ $T_A=25^{\circ}\text{C}$ Derate above 25°C	P_{tot}		300mW $2.4\text{mW}/^{\circ}\text{C}$
Operating Junction and Storage Temperature	T_j, T_{stg}	-55 to $+150^{\circ}\text{C}$	

ELECTRICAL CHARACTERISTICS ($T_A=25^{\circ}\text{C}$)

PARAMETER	SYMBOL	MIN	TYP	MAX	UNIT	TEST CONDITIONS
Collector-Emitter Breakdown Voltage	BV_{CE0}	30			V	$I_C=2\text{mA}$ $I_B=0$
Collector-Base Breakdown Voltage	BV_{CB0}	45			V	$I_C=10\mu\text{A}$ $I_E=0$
Emitter-Base Breakdown Voltage BC183,L BC213,L	BV_{EB0}	6 5			V	$I_E=10\mu\text{A}$ $I_C=0$
Collector Cutoff Current	I_{CB0}			15	nA	$V_{CB}=30\text{V}$ $I_E=0$
Emitter Cutoff Current	I_{EB0}			15	nA	$V_{EB}=4\text{V}$ $I_C=0$

MICRO ELECTRONICS LTD.

38 HUNG TO ROAD, KWUN TONG, HONG KONG. TELEX 43510
KWUN TONG P. O. BOX 69477 CABLE ADDRESS "MICROTRON"
TELEPHONE:- 3-430181-6, 3-893363, 3-892423, 3-898221
FAX: 3-410321

ELECTRICAL CHARACTERISTICS (TA=25°C)

Collector-Emitter Saturation BC183,L BC213,L	V _{CE(sat)}	0.07	0.25 0.6	V	I _C =10mA I _B =0.5mA I _C =100mA I _B =5mA*
Base-Emitter Saturation BC183,L BC213,L	V _{BE(sat)}		1.2 1.1	V	I _C =100mA I _B =5mA*
Base-Emitter Voltage BC183,L BC213,L	V _{BE}	0.55 0.6	0.7 0.72	V	V _{CE} =5V I _C =2mA
D.C. Current Gain BC183,L BC213,L BC183,L BC213,L	H _{FE}	100 220 140 130	120		V _{CE} =5V I _C =10μA V _{CE} =5V I _C =2mA V _{CE} =5V I _C =100mA*
Small Signal Current Gain (f=1KHz) BC183,L BC213,L Group A Group B Group C	h _{fe}	240 140 125 240 450	900 260 500 900		V _{CE} =5V I _C =2mA
Output Capacitance BC183,L BC213,L	C _{ob}	3 5	5	pF	V _{CB} =10V I _E =0 f=1MHz
Input Capacitance BC183,L	C _{ib}	9.5		pF	V _{EB} =0.5V I _E =0 f=1MHz
Current Gain-Bandwidth Product BC183,L BC213,L	f _T	280 350		MHz	I _C =10mA V _{CE} =5V f=100MHz
Noise Figure BC183,L BC213,L	NF		10	dB	I _C =200μA V _{CE} =5V R _G =2KΩ NB=15.7KHz f ₁ =10Hz f ₂ =10KHz

* Pulse Test : Pulse Width = 300μS, Duty Cycle ≤ 2%.