

Smart-UPS On-Line

APC Smart-UPS RT 5000VA 208V w/ 208V to 120V Step-Down Transformer

APC Smart-UPS On-Line, 3500 Watts / 5000 VA, Input 208V / Output 120V, 208V, Interface Port RJ-45 10/100 Base-T, RJ-45 Serial, SmartSlot, Extended runtime model, Rack Height 6 U

Includes: CD with software, Smart UPS signalling RS-232 cable, User Manual, Web/SNMP Management Card

Standard Lead Time: Usually in Stock

SURTD5000XLT-1TF3

Email Technical Specifications

Printer Friendly



[More Images](#)

Product Category

- Computer and Peripheral (6)
- Home UPS (1)
- Network and Server
- > Smart-UPS
- > Smart-UPS BR
- > **Smart-UPS On-Line**
- > Symmetra
- Data Center and Facility 3 Phase (15)
- Special Applications (5)
- UPS Management (7)

[Technical Specifications](#) [Product Overview](#) [Documentation](#) [Software & Firmware](#) [Options](#) [Ratings and Reviews](#)

[Return to Uninterruptible Power Supply \(UPS\)](#)

Output

Output Power Capacity	3500 Watts / 5000 VA
Max Configurable Power	3500 Watts / 5000 VA
Nominal Output Voltage	120V, 208V
Output Voltage Note	Configurable for 208 or 240 nominal output voltage
Efficiency at Full Load	91.0%
Output Voltage Distortion	Less than 3%
Output Frequency (sync to mains)	50/60 Hz +/- 3 Hz user adjustable +/- 0.1
Other Output Voltages	240
Crest Factor	3 : 1
Topology	Double Conversion Online
Waveform Type	Sine wave
Output Connections	(8) NEMA 5-20R
	(1) NEMA L14-30R
	(4) NEMA L6-20R
	(2) NEMA L6-30R
Bypass	Internal Bypass (Automatic and Manual)



Input

Nominal Input Voltage	208V
Input Frequency	50/60 Hz +/- 5 Hz (auto sensing)
Input Connections	NEMA L6-30P
Cord Length	3.05 meters
Input voltage range for main operations	160 - 280V
Input voltage adjustable range for mains operation	100 - 280V




Batteries & Runtime

Battery Type	Maintenance-free sealed Lead-Acid battery with suspended electrolyte : leakproof
Included Battery Modules	2
Typical recharge time	2.50 hour(s)
Replacement Battery	RBC44
RBC™ Quantity	1
Extended Run Options	APC Smart-UPS RT 5000VA 208V w/ 208V to 120V Step-Down Transformer

Runtime Graph

Curve	Part Number(s)
A	SURTD5000XLT-1TF3
B	SURTD5000XLT-1TF3 + (1)SURT192XLBP
C	SURTD5000XLT-1TF3 + (2)SURT192XLBP
D	SURTD5000XLT-1TF3 + (3)SURT192XLBP
E	SURTD5000XLT-1TF3 + (4)SURT192XLBP



Hover over the line on the graph above to view the runtime at any desired load

Curve fit to measured runtime data. All measurements taken with new, fully charged batteries, at typical environmental conditions, with no electrical input and balanced resistive load (PF = 1.0) output.

[View Enlarged Graph](#)

[View Runtime Chart](#)

Communications & Management

Interface Port(s)	RJ-45 10/100 Base-T, RJ-45 Serial, SmartSlot
Pre-Installed SmartSlot™ Cards	AP9631
Control panel	LED status display with load and battery bar-graphs and On Line : On Battery : Replace Battery : Overload and Bypass Indicators
Audible Alarm	Alarm when on battery : distinctive low battery alarm : overload continuous tone alarm
Emergency Power Off (EPO)	Yes

Surge Protection and Filtering

Surge energy rating	480 Joules
Filtering	Full time multi-pole noise filtering : 0.3% IEEE surge let-through : zero clamping response time : meets UL 1449

Physical

Maximum Height	432.00 mm
Maximum Width	259.00 mm
Maximum Depth	660.00 mm
Rack Height	6U
Net Weight	111.36 KG
Shipping Weight	127.28 KG
Shipping Height	658.00 mm
Shipping Width	603.00 mm
Shipping Depth	980.00 mm
Color	Black

Environmental

Operating Environment	0 - 40 °C
-----------------------	-----------

Operating Relative Humidity	0 - 95%
Operating Elevation	0-3000 meters
Storage Temperature	-15 - 45 °C
Storage Relative Humidity	0 - 95%
Storage Elevation	0-15000 meters
Audible noise at 1 meter from surface of 55.00 dBA unit	
Online Thermal Dissipation	1150.00 BTU/hr
Conformance	
Regulatory Approvals	CSA, FCC Part 15 Class A, UL 1778
Standard Warranty	2 years repair or replace
Sustainable Offer Status	

**The time to recharge to 90% of full battery capacity following a discharge to shutdown using a load rated for 1/2 the full load rating of the UPS.