


Shielded CHAMP Cable Connector Kits (Continued)

Inner Ferrule on Jacket


No. of Positions	Cable Diameter (Less Than)
24	.300 7.62
36	.350 8.89
50	.400 10.16



Inner Ferrule on Braid*

No. of Positions	Cable Diameter (Greater Than)
24	.300 7.62
36	.350 8.89
50	.400 10.16

* Ferrule size based on braid bundle diameter.



No. of Positions	Cable Range	Part Numbers					
		Shielded Plug Kit		Shielded Receptacle Kit		Cover Kits	
		B Slot	E Slot	B Slot	E Slot		
24	.250-.500 6.35-12.70	554948-45 554948-24	554948-33	—	—	—	554944-1
36	.250-.500 6.35-12.70	554951-2	—	554950-2	554950-1	—	554945-1
50	.350-.625 8.89-15.88	554945-26	554954-1	554953-21	554953-11	554955-2	554946-12 554946-2

¹ SCSI applicable.

² For cable diameter of .500 [12.70] or less use -1 kit. For cable diameter greater than .500 [12.70] use -2 kit.

³ Connector with M3.5 threads kits includes M3.5 x 2.00 [50.80] standoff stud.

⁴ 4-40 UNC-2B hole size.

⁵ M3.5 x 0.6-6G, shoulder stud screws (2) supplied.

⁶ Contact Tyco Electronics for RoHS Part Number information.

Typical Cable Assembly (Shielding Effectiveness)

