

● Part Numbering

Trimmer Potentiometers

(Part Number)

PV	Z3	A	103	A01	R00
①	②	③	④	⑤	⑥

① Product ID

Product ID	
PV	Trimmer Potentiometers

② Series

③ Adjustment Direction /Lead Type


Code	Series	Code	Adjustment Direction/ Lead Type
Z2	SMD Open 2mm Size Carbon Resistive Element	A	Top
		K	Rear
		R	Rear
A2	SMD Open 2mm Size	A	Top
Z3	SMD Open 3mm Size Carbon Resistive Element	A	Top
		G	Top
		K	Rear
		R	Rear
F2	SMD Sealed 2mm Size	A	Top
G3	SMD Sealed 3mm Size	A	Top, J-hook
		G	Top, Gull-wing
		K	Rear
M4	SMD Sealed 4mm Size	A	Top
G5	SMD Sealed 5mm Square 11-turns	A	Top
		H	Side
01	SMD Sealed 6mm Square 12-turns	P	Side
		W	Top
		X	Side
C6	Lead Sealed 6mm Square Single-turn	A	Top, Triangle
		D	Top, Triangle
		E	Side, Triangle
		G	Side, Triangle
		H	Side, Triangle
		M	Top, Inline
		Q	Side, Inline
32	Lead Sealed 6mm Round Single-turn	H	Top, Triangle
		P	Top, Triangle
		R	Top, Inline
		N	Side, Triangle
		T	Side, Triangle
		S	Side, Triangle
34	Lead Sealed 9mm Square Single-turn	F	Top, Triangle
		P	Top, Triangle
		H	Side, Triangle
		X	Side, Triangle
		W	Side, Inline
12	Lead Sealed 7mm Round 4-turns	H	Top, Triangle
		P	Top, Triangle
		T	Side, Triangle
		S	Side, Triangle


22	Lead Sealed 31mm Rectangular 22-turns	L	Side
		S	Side, Inline
		Y	Side, Triangle
23	Lead Sealed 19mm Rectangular 15-turns	P	Side, Triangle
		Y	Side, Triangle
36	Lead Sealed 10mm Square 25-turns	W	Top, Inline
		Y	Top, Triangle
		P	Side, Triangle
		X	Side, Inline
37	Lead Sealed 6mm Square 12-turns	Z	Side, Triangle
		W	Top, Triangle
		Y	Top, Inline
		P	Side, Triangle
		X	Side, Triangle
		Z	Side, Inline

④ Total Resistance

Expressed by three figures. The unit is ohm. The first and second figures are significant digits, and the third figure expresses the number of zeros which follow the two figures.

Ex.)	Code	Total Resistance
	100	10Ω
	102	1000Ω
	104	100000Ω (=100kΩ)

Continued on the following page. 

 Continued from the preceding page.

⑤ Individual Specification

Series	Code	Individual Specification Code
PVA2	A01	Standard Type
PVZ2	A01	Standard Type
	A04	Ultra-thin Type
	C01	High-heat Resistance Type
	C04	High-heat Resistance Type (for Ultra-thin Type)
PVZ3	A01	Standard Type (for Top Adjustment)
	C01	High-heat Resistance Type (for Top Adjustment)
	E01	High-heat Resistance Type (for Rear Adjustment)
PVM4	C01	Standard Type
	D01	High-liability Type
PVF2	A11	Standard Type (Resistance Change Characteristics: Linear)
	A41	Standard Type (Resistance Change Characteristics: Log Curve)
	A81	Standard Type (Resistance Change Characteristics: Log Curve)
	A51	Standard Type (Resistance Change Characteristics: Log-log Curve)
	A91	Standard Type (Resistance Change Characteristics: Log-log Curve)
PV32/PV12	A01	Standard Type
PVG3/PVG5/PV01/ PV22/PV23/ PV34/PV36/PV37	C01	Standard Type
PVC6	C01	Standard Type
	C04	Radial Taping
PV36/PV37	C01	Standard Type
	C31	Radial Taping

⑥ Packaging

Code	Packaging
A00	Ammo Pack
B00	Bulk
M00*	Magazine
R00	Reel

* M12 for PV36P Type and M15 for PV36W/Y/X/Z Type.