NEWA Coupled Inductors – MSD1260T

For high temperature applications



The MSD1260T series of shielded coupled inductors was designed specifically for high temperature applications – up to 125°C. The excellent coupling coefficient (k \ge 0.94) makes it ideal for use in SEPIC applications. In SEPIC topologies, the required inductance for each winding in a coupled inductor is half the value needed for two separate inductors, allowing selection of a part with lower DCR and higher current handling.

These parts provide high inductance, high efficiency and excellent current handling in a rugged, low cost part. They are well suited for use as VRM inductors in high-current DC-DC and VRM/VRD controllers.

They can also be used as two single inductors connected in series or parallel, or as 1 : 1 transformers.



Dimensions are in $\frac{inches}{mm}$







Terminations RoHS compliant matte tin over nickel over phos bronze. Other terminations available at additional cost.

Weight: 2.8-3.2 g

Core material Ferrite

Ambient temperature -40° C to $+125^{\circ}$ C with Irms current, $+125^{\circ}$ C to $+165^{\circ}$ C with derated current

Storage temperature Component: -40°C to +165°C. Packaging: -40°C to +80°C

Winding to winding isolation 500 Vrms

Resistance to soldering heat Max three 40 second reflows at +260°C, parts cooled to room temperature between cycles

Moisture Sensitivity Level (MSL) 1 (unlimited floor life at $<30^{\circ}$ C / 85% relative humidity)

Failures in Time (FIT) / Mean Time Between Failures (MTBF)38 per billion hours / 26,315,789 hours, calculated per Telcordia SR-332Packaging500/13" reel;Plastic tape:24 mm wide, 0.35 mm thick,16 mmpocket spacing, 6.6 mm pocket depth

PCB washing Only pure water or alcohol recommended



Specifications subject to change without notice. Please check our website for latest information.

Document 703-1 Revised 08/28/09

© Coilcraft, Inc. 2009

1102 Silver Lake Road Cary, Illinois 60013 **Phone** 847/639-6400 **Fax** 847/639-1469 **E-mail** info@coilcraft.com **Web** http://www.coilcraft.com



Typical SEPIC schematic Refer to Application Note, Document 639,

"Selecting Coupled Inductors for SEPIC Applications"



High Temperature Coupled Inductors for SEPIC – MSD1260T

								Irms(A)	
	Inductance ²		DCR max ³	SRF typ ⁴	Isat (A) ⁵			both	one
Part number ¹	()	IH)	(Ohms)	(MHz)	10% drop	20% drop	30% drop	windings ⁶	winding ⁷
MSD1260T-472ML_	4.7	7 ±20%	0.036	38.0	9.00	10.18	11.08	3.16	4.47
MSD1260T-562ML_	5.6	5 ±20%	0.040	30.0	8.00	9.06	9.84	3.00	4.24
MSD1260T-682ML_	6.8 ±20%		0.048	27.0	7.00	8.00	1.64	2.75	3.88
MSD1260T-822ML_	8.2	2 ±20%	0.052	26.0	6.44	7.38	7.98	2.63	3.72
MSD1260T-103ML_	10	±20%	0.060	22.0	5.40	6.32	6.88	2.45	3.46
MSD1260T-123ML_	12	±20%	0.074	20.0	5.30	6.18	6.70	2.21	3.12
MSD1260T-153ML_	15	±20%	0.085	18.0	4.60	5.30	5.80	2.06	2.92
MSD1260T-183ML_	18	±20%	0.097	16.0	4.50	5.22	5.68	1.93	2.73
MSD1260T-223ML_	22	±20%	0.116	15.0	4.00	4.62	5.02	1.76	2.49
MSD1260T-273ML_	27	±20%	0.124	13.0	3.60	4.14	4.50	1.70	2.41
MSD1260T-333ML_	33	±20%	0.134	12.4	3.30	3.80	4.14	1.64	2.32
MSD1260T-393ML_	39	±20%	0.142	12.0	3.00	3.48	3.82	1.59	2.25
MSD1260T-473ML_	47	±20%	0.174	11.6	2.70	3.12	3.40	1.44	2.03
MSD1260T-563ML_	56	±20%	0.198	10.5	2.50	2.90	3.14	1.35	1.91
MSD1260T-683ML_	68	±20%	0.216	10.0	2.30	2.66	2.88	1.29	1.83
MSD1260T-823ML_	82	±20%	0.274	8.6	2.10	2.40	2.60	1.15	1.62
MSD1260T-104ML_	100	±20%	0.322	7.8	1.90	2.18	2.38	1.06	1.50
MSD1260T-124KL_	120	±10%	0.418	6.8	1.60	1.84	2.04	0.93	1.31
MSD1260T-154KL_	150	±10%	0.476	6.4	1.50	1.76	1.92	0.87	1.23
MSD1260T-184KL_	180	±10%	0.536	6.1	1.40	1.64	1.78	0.82	1.16
MSD1260T-224KL_	220	±10%	0.691	5.5	1.30	1.48	1.60	0.72	1.02
MSD1260T-274KL_	270	±10%	0.806	4.3	1.10	1.30	1.40	0.67	0.95
MSD1260T-334KL_	330	±10%	1.09	4.0	1.00	1.16	1.26	0.57	0.81
MSD1260T-394KL_	390	±10%	1.20	3.6	0.950	1.11	1.23	0.55	0.77
MSD1260T-474KL_	470	±10%	1.59	3.0	0.900	0.994	1.09	0.48	0.67
MSD1260T-564KL_	560	±10%	1.81	2.8	0.800	0.908	0.948	0.45	0.63
MSD1260T-684KL_	680	±10%	2.06	2.6	0.700	0.804	0.874	0.42	0.59
MSD1260T-824KL_	820	±10%	2.65	2.5	0.640	0.732	0.802	0.37	0.52
MSD1260T-105KL_	1000	±10%	3.06	2.4	0.590	0.674	0.728	0.34	0.49

1. When ordering, please specify termination and packaging codes:

MSD1260T-105K L D

- Termination: L = RoHS compliant matte tin over nickel over phos bronze. Special order: T = RoHS tin-silver-copper (95.5/4/0.5) or S = non-RoHS tin-lead (63/37).
- Packaging: D = 13" machine-ready reel. EIA-481 embossed plastic tape (500 parts per full reel).

 \mathbf{B} = Less than full reel. In tape, but not machine ready. To have a leader and trailer added (\$25 charge), use code letter D instead.

- Inductance shown for each winding, measured at 100 kHz, 0.1 Vrms, 0 Adc on an Agilent/HP 4284A LCR meter or equivalent. When leads are connected in parallel, inductance is the same value. When leads are connected in series, inductance is four times the value.
- DCR is for each winding. When leads are connected in parallel, DCR is half the value. When leads are connected in series, DCR is twice the value.
- 4. SRF measured using an Agilent/HP 4191A or equivalent. When leads are connected in parallel, SRF is the same value.
- DC current, at which the inductance drops the specified amount from its value without current. It is the sum of the current flowing in both windings.
- Equal current when applied to each winding simultaneously that causes a 40°C temperature rise from 25°C ambient. See temperature rise calculation.
- Maximum current when applied to one winding that causes a 40°C temperature rise from 25°C ambient. See temperature rise calculation.
- 8. Electrical specifications at 25°C.

Refer to Doc 639 "Selecting Coupled Inductors for SEPIC Applications." Refer to Doc 362 "Soldering Surface Mount Components" before soldering.

Coilcraft_

Specifications subject to change without notice. Please check our website for latest information.

Document 703-2 Revised 08/28/09

1102 Silver Lake Road Cary, Illinois 60013 Phone 847/639-6400 Fax 847/639-1469 E-mail info@coilcraft.com Web http://www.coilcraft.com

Temperature rise calculation based on specified Irms

 $\begin{array}{l} \mbox{Winding power loss} = (I_{L1}^2 + I_{L2}^2) \times \mbox{DCR in Watts (W)} \\ \mbox{Temperature rise } (\Delta t) = \mbox{Winding power loss} \times \frac{55.6^\circ C}{W} \\ \mbox{} \Delta t = (I_{L1}^2 + I_{L2}^2) \times \mbox{DCR} \times \frac{55.6^\circ C}{W} \\ \end{array}$

Example 1. MSD1260T-153ML (Equal current in each winding) Winding power loss = $(2.06^2 + 2.06^2) \times 0.085 = 0.721$ W $\Delta t = 0.721$ W $\times \frac{55.6^{\circ}C}{W} = 40^{\circ}C$

Example 2. MSD1260T-153ML ($I_{L1} = 2.4 \text{ A}$, $I_{L2} = 1.3 \text{ A}$) Winding power loss = (2.4² + 1.3²) × 0.085 = 0.633 W

$$\Delta t = 0.633 \text{ W} \times \frac{55.6^{\circ}\text{C}}{\text{W}} = 35.2^{\circ}\text{C}$$

Coupled Inductor Core and Winding Loss Calculator

This web-based utility allows you to enter frequency, peak-to-peak (ripple) current, and Irms current to predict temperature rise and overall losses, including core loss. Visit www.coilcraft.com/coupledloss.

NEW: High Temperature Coupled Inductors for SEPIC – MSD1260T



Typical L vs Frequency



Current Derating



Coilcraft

Specifications subject to change without notice. Please check our website for latest information.

Document 703-3 Revised 08/28/09

1102 Silver Lake Road Cary, Illinois 60013 Phone 847/639-6400 Fax 847/639-1469 E-mail info@coilcraft.com Web http://www.coilcraft.com