

INTERCONNECTS

SERIES 850, 851, 852, 853 • .050" GRID SURFACE MOUNT HEADERS AND SOCKETS • SINGLE AND DOUBLE ROW STRIPS




FIG. 1




FIG. 2




FIG. 3




FIG. 4

- Single row interconnects having an even number of pins are now available with a left or right hand footprints
- Headers (850 and 852) use MM #4006 pins. See page 208 for details
- Sockets (851 and 853) use MM #4890-0 receptacles and accept pin diameters from .015"-.021". See page 160 for details
- Receptacles use Hi-Rel, 3-finger BeCu #11 contact rated at 3 amps. See page 251 for details
- Insulators are high temperature thermoplastic, suitable for all soldering operations



ORDERING INFORMATION

FIG. 1L	Single Row Header, Left Hand Footprint, Odd or Even # of Pins							
	850-XX-0-30-001000 Specify number of pins 02-50							
FIG. 1R	Single Row Header, Right Hand Footprint, Even # of Pins							
	850-XX-0-30-002000 Specify number of pins 02-50							
FIG. 2	Double Row Header, Even # of Pins							
	852-XX-30-001000 Specify number of pins 004-100							
SPECIFY PLATING CODE XX=		10	90	40				
Pin Plating		10 μ" Au	200 μ" Sn/Pb	200 μ" Sn				
FIG. 3L	Single Row Socket, Left Hand Footprint, Odd or Even # of Pins							
	851-XX-0-30-001000 Specify number of pins 02-50							
FIG. 3R	Single Row Socket, Right Hand Footprint, Even # of Pins							
	851-XX-0-30-002000 Specify number of pins 02-50							
FIG. 4	Double Row Socket, Even # of Pins							
	853-XX-30-001000 Specify number of pins 004-100							
XX=Plating Code See Below For Electrical, Mechanical & Environmental Data, See page 264								
SPECIFY PLATING CODE XX=			91	93	99	41	43	44
Sleeve (Pin)			200 μ" Sn/Pb	200 μ" Sn/Pb	200 μ" Sn/Pb	200 μ" Sn	200 μ" Sn	200 μ" Sn
Contact (Clip)			10 μ" Au	30 μ" Au	100 μ" Sn/Pb	10 μ" Au	30 μ" Au	100 μ" Sn

★ 44 Plating Non-Standard



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Mill-Max:

[853-99-100-30-001000](#) [851-99-050-30-001000](#) [850-90-050-30-001000](#) [850-10-050-30-001000](#) [852-90-016-30-001000](#) [853-43-100-30-001000](#) [852-10-100-30-001000](#) [852-90-100-30-001000](#) [851-93-050-30-001000](#) [853-93-100-30-001000](#) [850-90-036-30-001000](#) [852-40-100-30-001000](#) [850-40-050-30-001000](#) [851-43-050-30-001000](#) [852-10-010-30-001000](#) [850-10-050-30-002000](#) [850-40-050-30-002000](#) [850-90-050-30-002000](#) [851-43-050-30-002000](#) [851-44-050-30-002000](#) [851-93-050-30-002000](#) [851-99-050-30-002000](#) [851-93-003-30-001000](#)