

Cylindrical Fuses

500 Volts • 0.5 – 100 Amperes




Littelfuse fast acting (gL-gG) fuses are used for the protection of cables against short-circuits. Time-lag (aM) fuses are used for protection of motors.

Specifications

Standards: IEC 269-2-1
Example part number: CY22X58G50

Size	Current Range	Voltage AC	Interrupting Rating
10 x 38 mm	0.5-32A	500V	120kA
14 x 51 mm	2-50A	500V	80kA
22 x 58 mm	16-100A	500V	80kA



Amperage	gL-gG			aM		
	10X38	14X51	22X58	10X38	14X51	22X58
0.5	CY10X38G.5	—	—	CY10X38M.5	—	—
1	CY10X38G1	—	—	CY10X38M1	—	—
2	CY10X38G2	CY14X51G2	—	CY10X38M2	CY14X51M2	—
4	CY10X38G4	CY14X51G4	—	CY10X38M4	CY14X51M4	—
6	CY10X38G6	CY14X51G6	—	CY10X38M6	CY14X51M6	—
8	CY10X38G8	CY14X51G8	—	CY10X38M8	CY14X51M8	—
10	CY10X38G10	CY14X51G10	—	CY10X38M10	CY14X51M10	—
12	CY10X38G12	CY14X51G12	—	CY10X38M12	CY14X51M12	—
16	CY10X38G16	CY14X51G16	CY22X58G16	CY10X38M16	CY14X51M16	CY22X58M16
20	CY10X38G20	CY14X51G20	CY22X58G20	CY10X38M20	CY14X51M20	CY22X58M20
25	CY10X38G25	CY14X51G25	CY22X58G25	CY10X38M25	CY14X51M25	CY22X58M25
32	CY10X38G32	CY14X51G32	CY22X58G32	CY10X38M32	CY14X51M32	CY22X58M32
40	—	CY14X51G40	CY22X58G40	—	CY14X51M40	CY22X58M40
50	—	CY14X51G50	CY22X58G50	—	CY14X51M50	CY22X58M50
63	—	—	CY22X58G63	—	—	CY22X58M63
80	—	—	CY22X58G80	—	—	CY22X58M80
100	—	—	CY22X58G100	—	—	CY22X58M100
Dimensions (mm)	A	10	14	10	14	22
	B	38	51	58	51	58

Fuseholders

Part No.	Size	# of Poles	Amp Rating	Voltage	Terminal Type
CYH10381	10X38	1	32A	690V	Pressure Plate
CYH10382	10X38	2	32A	690V	Pressure Plate
CYH10383	10X38	3	32A	690V	Pressure Plate
CYH10381ID*	10X38	1	32A	690V	Pressure Plate
CYH14511	14X51	1	50A	690V	Pressure Plate
CYH14512	14X51	2	50A	690V	Pressure Plate
CYH14513	14X51	3	50A	690V	Pressure Plate
CYH22581	22X58	1	125A	690V	Pressure Plate
CYH22582	22X58	2	125A	690V	Pressure Plate
CYH22583	22X58	3	125A	690V	Pressure Plate

* Indicating

NOTE: All fuseholders are DIN-Rail mountable.

Contact factory for dimensional information.

Multi-pole Assembly Kit



Assembly kit is designed for use with CYH1038 and LPSC/LPSM fuse holders. Kit contains 20 connector pincers and 10 handle pins.

Part No: CYHP001

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Littelfuse:

[CY14X51G2](#) [CY22X58G40](#) [CY22X58G80](#) [CY22X58G20](#) [CY22X58G25](#) [CY22X58G63](#) [CY22X58G16](#)
[CY22X58G50](#) [CY22X58G32](#) [CY10X38M32](#) [CY10X38G1](#) [CY10X38G2](#) [CY10X38G6](#) [CY10X38G8](#) [CY10X38G4](#)
[CY10X38M6](#) [CY10X38M2](#) [CY10X38M4](#) [CY10X38M8](#) [CY10X38M1](#) [CY10X38G32](#) [CY10X38G16](#) [CY10X38G12](#)
[CY10X38G10](#) [CY10X38G05](#) [CY10X38G20](#) [CY10X38G25](#) [CYH10381ZXID](#) [CY22X58M50](#) [CY22X58M16](#)
[CYH14512Z](#) [CY22X58M32](#) [CY22X58M63](#) [CYH14513Z](#) [CY22X58M25](#) [CY22X58M20](#) [CYH14511Z](#) [CY22X58M40](#)
[CY22X58M80](#) [CYHP0001Z](#) [CYH10382Z](#) [CYH10381Z](#) [CYH10383Z](#) [CY14X51M2](#) [CY14X51M6](#) [CY14X51M8](#)
[CY14X51M4](#) [CY14X51G8](#) [CY14X51G4](#) [CY14X51G6](#) [CY14X51M32](#) [CY22X58M100](#) [CY14X51M50](#) [CY14X51M16](#)
[CY14X51M12](#) [CY14X51M10](#) [CY14X51M40](#) [CY14X51M20](#) [CY14X51M25](#) [CY14X51G25](#) [CY14X51G20](#)
[CY14X51G40](#) [CY14X51G32](#) [CY14X51G16](#) [CY14X51G12](#) [CY14X51G10](#) [CY14X51G50](#) [CYH22582Z](#) [CYH22583Z](#)
[CY22X58G100](#) [CYH22581Z](#) [CY10X38M05](#) [CY10X38M25](#) [CY10X38M20](#) [CY10X38M16](#) [CY10X38M12](#)
[CY10X38M10](#)