


PIN RECEPTACLES

FOR .020" - .032" DIAMETER PINS

0338

0338-0-15-XX-15-XX-10-0


Solder mount in .057 min. mounting hole
Also available on 16mm wide carrier tape:
1,700 parts per 13" reel
Order as: 0338-0-57-XX-15-XX-10-0



0378

0378-0-15-XX-15-XX-10-0


Solder mount in .082 min. mounting hole



6002

6002-0-19-XX-15-XX-10-0


Solder mount in .059 min. mounting hole
Wire Termination. Accepts wire sizes
26 AWG Max. / 30 AWG Min.



7009

7009-0-19-XX-15-XX-10-0


Press-fit in .063 min. mounting hole
Wire Termination. Accepts wire sizes
22 AWG Max. / 26 AWG Min.



0339

0339-0-15-XX-15-XX-10-0


Solder mount in .057 min. mounting hole
Also available on 24mm wide carrier tape:
1,540 parts per 13" reel
Order as: 0339-0-57-XX-15-XX-10-0



5200

5200-0-19-XX-15-27-10-0

Surface mount on a .103" dia. P.C.B. pad



SPECIFICATIONS:

Shell Material: Brass Alloy 360, 1/2 Hard

Contact Material: Beryllium Copper Alloy 172, HT

Dimensions: Inches

Tolerances On: Lengths: $\pm .005$

Diameters: $\pm .002$

Angles: $\pm 2^\circ$



ORDER CODE: XXXX - X - XX - XX - 15 - XX - 10 - 0

BASIC PART #

SPECIFY SHELL FINISH:

01 200 μ " TIN/LEAD OVER NICKEL

◆ 80 200 μ " TIN OVER NICKEL (RoHS)

◆ 15 10 μ " GOLD OVER NICKEL (RoHS)

SPECIFY CONTACT FINISH:

01 200 μ " TIN/LEAD OVER NICKEL

◆ 80 200 μ " TIN OVER NICKEL (RoHS)

◆ 27 30 μ " GOLD OVER NICKEL (RoHS)

SELECT CONTACT:

#15 CONTACT (DATA ON PAGE 254)

(For alternate contact choices, see group K on page 248)



Mill-Max Mfg. Corp. • 190 Pine Hollow Road, P.O. Box 300, Oyster Bay, NY 11771 • 516-922-6000 • Fax: 516-922-9253 • www.mill-max.com

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Mill-Max:

[6002-0-19-01-15-27-10-0](#) [0378-0-15-01-15-01-10-0](#) [0378-0-15-01-15-27-10-0](#) [0338-0-15-01-15-01-10-0](#) [0338-0-15-01-15-27-10-0](#) [0338-0-15-15-15-27-10-0](#) [0378-0-15-15-15-27-10-0](#) [7009-0-19-15-15-27-10-0](#) [6002-0-19-00-00-00-10-0](#) [0378-0-15-00-00-00-10-0](#) [0338-0-15-80-15-14-10-0](#) [0339-0-15-80-15-27-10-0](#) [0378-0-15-01-15-14-10-0](#) [0378-0-15-80-15-14-10-0](#) [7009-0-19-80-15-14-10-0](#) [7009-0-19-15-15-14-10-0](#) [7009-0-19-01-15-14-10-0](#) [6002-0-19-80-15-14-10-0](#) [6002-0-19-01-15-14-10-0](#)