

## Datasheet

### **RS Pro Lighting Controller Detector, PIR, Ceiling mount, 230 V ac, 76mm diameter**

**RS Stock No: 711-8580**



## Product Details

RS Pro lighting controller detector uses a PIR motion sensor combined with RF transceiver and two output channels to control incandescent, fluorescent and CFL lights. The output channel 2 provides dimmable control of 1 to 10 V ballasts in order to implement a maintained illuminance (constant light) system. The ceiling mount device has a voltage rating of 230 V ac.

## Features and Benefits

- Wireless PIR motion sensors function as a presence or absence detector
- Includes stored scenes for versatile manual on/off control of lighting
- Dimming control
- 7.8 x 2.8 m range



ENGLISH

### Specifications:

Controller Type	Detector
Diameter	76 mm
Dimmable	Yes
Height	61.2 mm
Mount Type	Ceiling
Range	7.8 x 2.8 m
Sensor Type	PIR
Time Delay	10 s to 99 min
Voltage Rating	230 V ac