| Features | 10W in 2" x 1" Package 2kVDC and 3kVDC Isolation Options | |
|------------|---|--|
| | • 2:1 or 4:1 Input Voltage Range | |
| Regulated | Continuous Short Circuit Protection | |
| Converters | (power limiting) | |
| | Synchronous Rectification on all Del outputs | |
| | Full SMD internal design | |
| | Remote Control Pin | |

• Efficiency to 87%

Description

The REC10-xxxxS_D/M -series offer single and dual regulated outputs in a 2"x1" package with 2kVDC or 3kVDC isolation options and are suitable for higher power industrial applications. Remote on/off control is standard. The converters can deliver 150% rated power for short periods of time to cope with applications with large capacitive loads or high start up currents.

Selection Guide

| Part Number | Input Voltage (VDC) | Output Voltage (VDC) | Output Current (mA) | Efficiency (typ.) (%) | Max. Cap. Load |
|---------------------------------|---------------------------|--|---------------------------|-----------------------------|-------------------|
| REC10-xx3.3S/H*/M | 9-18, 18-36, 36-75 | 3.3 | 2000 | 83-84 | 2200µF |
| REC10-xx05S/H*/M | 9-18, 18-36, 36-75 | 5 | 2000 | 86-87 | 2200µF |
| REC10-xx12S/H*/M | 9-18, 18-36, 36-75 | 12 | 833 | 85-86 | 2200µF |
| REC10-xx15S/H*/M | 9-18, 18-36, 36-75 | 15 | 667 | 85-86 | 2200µF |
| REC10-xx05D/H*/M | 9-18, 18-36, 36-75 | ±5 | ±1000 | 82-83 | ±1000µF |
| REC10-xx12D/H*/M | 9-18, 18-36, 36-75 | ±12 | ±416 | 85-86 | ±1000µF |
| REC10-xx15D/H*/M | 9-18, 18-36, 36-75 | ±15 | ±333 | 85-86 | ±1000µF |
| REC10-xx3.3SZ/H*/M | 9-36, 18-75 | 3.3 | 2000 | 82 | 2200µF |
| REC10-xx05SZ/H*/M | 9-36, 18-75 | 5 | 2000 | 86 | 2200µF |
| REC10-xx12SZ/H*/M | 9-36, 18-75 | 12 | 833 | 85 | 2200µF |
| REC10-xx15SZ/H*/M | 9-36, 18-75 | 15 | 667 | 86 | 2200µF |
| REC10-xx05DZ/H*/M | 9-36, 18-75 | ±5 | ±1000 | 82 | ±1000µF |
| REC10-xx12DZ/H*/M | 9-36, 18-75 | ±12 | ±416 | 85 | ±1000µF |
| REC10-xx15DZ/H*/M | 9-36, 18-75 | ±15 | ±333 | 86 | ±1000µF |
| * Standard is /H2 for 2kVDC isc | lation, | 2: | 1 | | 4:1 |
| use /H3 for 3kVDC Isolation | > | x = 9-18 Vin x = 18-36 Vin x = 36-75 Vi | n = 24, | xx = 9-36 xx = 18-7 | , |

ECONOLINE DC/DC-Converter

with 3 year Warranty



10 Watt 2" x 1" Single & Dual Output



RoHS 2011/65/EU 6/6 E-224736

EN-60950-1 Certified EN-60601-1 Certified UL-60950-1 Certified



Specifications (measured at $T_A = 25^{\circ}$ C, nominal input voltage, full load and after warm-up)

| · · A | · · · · · · · · · · · · · · · · · · · | • • • |
|---------------------------------------|---------------------------------------|---------------------|
| Input Voltage Range | | 2:1 or 4:1 |
| Input Filter | | PI Network |
| Output Voltage Accuracy (the Output 3 | 3.3V is ±1.2% max.) | ±1.0% max. |
| Line Voltage Regulation | | ±0.3% max. |
| Load Voltage Regulation | Single | ±0.5% max. |
| (25% to 100% full load) | Dual | ±1.2% max. |
| Cross Regulation (100%: 25% to 10 | 0% full load) | ±5% max. |
| Output Ripple and Noise (with 100n o | utput capacitor and 20MHz BW) | 100mVp-p max. |
| Start-up time (Nom. Vin at 100% Load | (b | 25ms typ. |
| Operating Frequency (Full Load) | | 300kHz typ. |
| Efficiency (Nom. Vin at 100% Load) | | see Selection Guide |
| Minimum Load | | 0% |
| Input Surge Voltage (100ms max.) | 12V Input | 36VDC |
| | 24V Input | 50VDC |
| | 48V Input | 100VDC |
| | | |

continued on next page

Refer to Application Notes

**Any data referred to in this datasheet are of indicative nature and based on our practical experience only. For further details,

please refer to our Application Notes.

REC10-S_D/H*/M Series

2000VDC

3000VDC

1200pF typ.

1000VAC / 60Hz

1500VAC / 60Hz

DC-DC on 8.3VDC, DC-DC off 7.9VDC

DC-DC on 17.4VDC, DC-DC off 16.7VDC

DC-DC on 35.7VDC, DC-DC off 34.3VDC

DC-DC on 17.4VDC, DC-DC off 16.7VDC

DC-DC on 8.3VDC, DC-DC off 7.9VDC

ECONOLINE DC/DC-Converter

Isolation Voltage

Under Voltage Lockout (2:1)

Under Voltage Lockout (4:1)

Isolation Capacitance

Specifications cont. (measured at T_A = 25°C, nominal input voltage, full load and after warm-up)

(tested for 1 second) (rated for 1 minute)

(tested for 1 second)

(rated for 1 minute)

12V Input

24V Input

48V Input

24V Input

48V Input

H2-Suffix

H3-Suffix

Derating-Graph

(Ambient Temperature)

2:1 Converters



4:1 Converters





| isolation oapacitance | izoopi typ. |
|--|--|
| Isolation Resistance | 1 GΩ min. |
| Overload Protection | 150% typ. |
| Short Circuit Protection | Continuous, Auto Restart |
| Operating Temperature Range | 4:1 -40°C to +71°C (see Graph) |
| (free air convection) | 2:1 -40°C to +81°C (see Graph) |
| Storage Temperature Range | -55°C to +105°C |
| Remote On/Off | DC/DC ON Open or 3.5V <vr<12v< td=""></vr<12v<> |
| | DC/DC OFF Short or 0V <vr<1.2v< td=""></vr<1.2v<> |
| Temperature Coefficient | ±0.05% max. |
| Relative Humidity | 95% RH |
| Case Material | Nickel Plated Metal with Non-Conductive Base |
| Thermal Impedance | Natural convection 12°C/W |
| Maximum Case Temperature | 100°C |
| Vibration | 10-55Hz, 2G, 30mins along X,Y & Z |
| Package Weight | 27g |
| Packing Quantity | 10 pcs per Tube |
| MTBF (+25°C) ↓ Detailed Information see | using MIL-HDBK 217F >1000 x 10 ³ hours |
| (+71°C) ∫ Application Notes chapter "MT | F'' using MIL-HDBK 217F >250 x 10 ³ hours |
| Certifications | |
| EN General Safety Report: SPCLVD12 | 1033-2 EN60950-1:2006 + A12:2011 |
| UL General Safety Report: E224736 | UL 60950-1 1st Ed. |
| | C22.2 No. 60950-1-03 |

EN Medical Safety Report: MDD12060585 + RM1206085 IEC/EN 60601-1 3rd Edition; Medical Report + IS014971 Risk Assessment

Note: Refer to Application Notes for EMC Class B Filter suggestion

Package Style and Pinning (mm)



2" x 1" Package



| - | 25.4 |
|---------------|----------------------|
| ↓ 5.6 1 | → + 2.50 → + 5.08 |

| Pin # | Single | Dual |
|-------|--------|-------|
| 1 | +Vin | +Vin |
| 2 | –Vin | –Vin |
| 3 | +Vout | +Vout |
| 4 | No Pin | Com |
| 5 | -Vout | -Vout |
| 6 | CTRL | CTRL |

The product information and specifications are subject to change without prior notice. RECOM products are not authorized for use in safety-critical applications (such as life support) without RECOM's explicit written consent. A safety-critical application is defined as an application where a failure of a RECOM product may reasonably be expected to endanger or cause loss of life, inflict bodily harm or damage property. The buyer shall indemnify and hold harmless RECOM, its affiliated companies and its representatives against any damage claims in connection with the unauthorized use of RECOM products in such safety-critical applications.