



500-047 EMI/RFI Elliptical Entry Micro-D Banding Backshell



Elliptical Backshells provide extra room for large wire bundles. This one piece version features an oversize shield termination area for both standard and micro BandMaster™ ATS shield termination straps.


Materials

- Shell: Aluminum Alloy 6061 -T6
- Clips: 17-7PH Stainless Steel
- Hardware: 300 Series Stainless Steel

How To Order EMI/RFI Elliptical Backshells

Sample Part Number		500-047	M	25	H	T
Series	500-047					
Shell Finish	E – Chem Film (Alodyne) J – Cadmium, Yellow Chromate M – Electroless Nickel NF – Cadmium, Olive Drab Z2 – Gold					
Connector Size	09, 15, 21, 25, 31, 37 51, 51-2, 67, 69, 100 (See Table I)					
Hardware Option	B – Fillister Head Jackscrew H – Hex Head Jackscrew E – Extended Jackscrew F – Jackpost, Female (See Table I)					
EMI Band Strap Option	Omit (Leave Blank) – Band Not Included B – Standard Band .250" Wide, uncoiled M – Micro Band .125" Wide, uncoiled					
Qwik-Ty Option	T – with Qwik-Ty Omit for none					

Table I: Dimensions



Hardware Option	
	B - Fillister Head Jackscrew
	H - Hex Head Jackscrew
	E - Extended Jackscrew
	F - Jackpost, Female

Size	A		B		C		D Dia		E Dia		F		G		H Ref.		J Thread
	In.	mm.	In.	mm.	In.	mm.	In.	mm.	In.	mm.	In.	mm.	In.	mm.	In.	mm.	
09	.775	19.69	.34	8.64	.75	19.05	.312	7.92	.281	7.14	.32	8.13	.565	14.35	.154	3.91	2-56 UNC-2A
15	.925	23.50	.34	8.64	.88	22.35	.420	10.67	.281	7.14	.44	11.18	.715	18.16	.154	3.91	2-56 UNC-2A
21	1.075	27.31	.34	8.64	1.00	25.40	.590	14.99	.281	7.14	.56	14.22	.865	21.97	.154	3.91	2-56 UNC-2A
25	1.175	29.85	.34	8.64	1.06	26.92	.690	17.53	.281	7.14	.62	15.75	.965	24.51	.154	3.91	2-56 UNC-2A
31	1.325	33.66	.34	8.64	1.12	28.45	.820	20.83	.281	7.14	.68	17.27	1.115	28.32	.154	3.91	2-56 UNC-2A
37	1.475	37.47	.34	8.64	1.16	29.46	.970	24.64	.281	7.14	.72	18.29	1.265	32.13	.154	3.91	2-56 UNC-2A
51	1.425	36.20	.38	9.65	1.19	30.23	.920	23.37	.312	7.92	.75	19.05	1.215	30.86	.154	3.91	2-56 UNC-2A
51-2	1.835	46.61	.34	8.64	1.19	30.23	1.030	26.16	.281	7.14	.75	19.05	1.615	41.02	.154	3.91	2-56 UNC-2A
69	1.730	43.94	.40	10.16	1.19	30.23	1.190	30.23	.312	7.92	.75	19.05	1.515	38.48	.154	3.91	2-56 UNC-2A
100	2.160	54.86	.43	10.92	1.25	31.75	1.290	32.77	.360	9.14	.81	20.57	1.800	45.72	.184	4.67	4-40 UNC-2A

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Glenair:

[500-047M15BB](#) [500-047M15FB](#) [500-047C15B](#) [500-047J100B](#) [500-047J15HB](#) [500-047J31HB](#) [500-047J37B](#) [500-047J51B](#) [500-047J51E](#) [500-047M09BB](#) [500-047M09E](#) [500-047M09F](#) [500-047M09H](#) [500-047M09HB](#) [500-047M100HB](#) [500-047M15B](#) [500-047M15HB](#) [500-047M21H](#) [500-047M25B](#) [500-047M25EB](#) [500-047M25H](#) [500-047M31H](#) [500-047M37BB](#) [500-047M37H](#) [500-047M51B](#) [500-047M51E](#) [500-047M51H](#) [500-047M51HB](#) [500-047MA09HB-401](#) [500-047MA25HB-401](#) [500-047MA51HB-401](#) [500-047NF100B](#) [500-047NF15H](#) [500-047NF25H](#) [500-047M100H](#) [500-047M15H](#) [500-047J25HB](#) [500-047M100B](#) [500-047M100F](#) [500-047M31E](#) [500-047M37FB](#) [500-047M51F](#) [500-047M09B](#) [500-047M51BB](#) [500-047J100HB](#) [500-047J37HB](#) [500-047J51HB](#) [500-047M09EB](#) [500-047M09HBT](#) [500-047M100E](#) [500-047M15E](#) [500-047M25BB](#) [500-047M25E](#) [500-047M25FB](#) [500-047M37E](#) [500-047M51FB](#) [500-047MA15HB-401](#) [500-047NF51B](#) [500-047NF51EB](#) [500-047NF37E](#) [500-047NF37EB](#) [500-047M25EM](#) [500-047M09BM](#) [500-047M51HBT](#) [500-047M15HBT-678](#) [500-047M09HBT-678](#) [500-047M31HBT](#) [500-047M25HBT-678](#) [500-047M37EM](#) [500-047NFP25HBT-678](#) [500-047NFP09HBT-678](#) [500-047MA21HB-401](#) [500-047M69H](#) [500-047M21E](#) [500-047NF100H](#) [500-047M15F](#) [500-047M51HM](#) [500-047M31EB](#) [500-047M15HBT](#) [500-047M21EM](#) [500-047NF51H](#) [500-047M69HB](#) [500-047M21BB](#) [500-047NF09EB](#) [500-047M100BB](#) [500-047M09H-401](#) [500-047M51-2HB](#) [500-047NF37EM](#) [500-047M100EB](#) [500-047NF15EB](#) [500-047M31HB](#) [500-047M51EB](#) [500-047M37HB](#) [500-047M31B](#) [500-047M21HBT](#) [500-047M21B](#) [500-047NF25BB](#) [500-047M21HB](#) [500-047M25HB](#) [500-047NF69BB](#)